



Dynamic Braking Resistors for Rockwell PowerFlex Drives

Units come standard with a mill-galvanized indoor enclosure, terminal block (or cable landing) and normally closed thermal switch.

Available options:

- Painted Enclosure (-PC)
- Galvanized Outdoor Enclosure (-W)
- Painted Outdoor Enclosure (-PW)
- UL, CSA, or CE – Call Post Glover

PowerFlex 4

Standard Resistors									
Input Voltage (VAC)	HP	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
240	0.25	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
240	0.25	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
240	0.25	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
240	0.25	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
240	0.5	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	1	100%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	110%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	125%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	150%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1.5	100%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1.5	110%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1.5	125%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1.5	150%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	2	100%	67	T67R360W	T67R360W	T67R360W	T67R720W	T67R1K08	T67R1K8
240	2	110%	67	T67R360W	T67R360W	T67R360W	T67R720W	T67R1K08	T67R1K8
240	2	125%	67	T67R360W	T67R360W	T67R360W	T67R720W	T67R1K08	T67R1K8
240	2	150%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
240	3	100%	53	T53R360W	T53R360W	T53R360W	T53R720W	T53R1K44	T53R2K88
240	3	110%	53	T53R360W	T53R360W	T53R360W	T53R720W	T53R1K44	T53R2K88
240	3	125%	48	T48R360W	T48R360W	T48R360W	T48R720W	T48R1K44	T48R2K52
240	5	100%	32	T32R360W	T32R360W	T32R720W	T32R1K08	T32R2K88	T32R4K0
240	5	110%	32	T32R360W	T32R360W	T32R720W	T32R1K08	T32R2K88	T32R4K0
240	5	125%	32	T32R360W	T32R360W	T32R720W	*	*	*

PowerFlex 4

Standard Resistors									
Input Voltage (VAC)	HP	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
480	0.5	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	0.5	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	0.5	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	0.5	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	1	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	2	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
480	2	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
480	2	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
480	2	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
480	3	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	5	100%	121	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K52	T121R5K61
480	5	110%	121	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K52	T121R5K61
480	5	125%	121	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K52	T121R5K61
480	5	150%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K88	T97R4K32

PowerFlex 40

Standard Resistors									
Input Voltage (VAC)	HP	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
240	0.5	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	1	100%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	110%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	125%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	150%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1.5	100%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K44
240	1.5	110%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K44
240	1.5	125%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K44
240	1.5	150%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K44
240	2	100%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
240	2	110%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
240	2	125%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
240	2	150%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
240	3	100%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	3	110%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	3	125%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	3	150%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	5	100%	23	T23R360W	T23R360W	T23R720W	T23R1K08	T23R2K88	T23R4K98
240	5	110%	23	T23R360W	T23R360W	T23R720W	T23R1K08	T23R2K88	T23R4K98
240	5	125%	23	T23R360W	T23R360W	T23R720W	T23R1K08	T23R2K88	T23R4K98
240	5	150%	23	T23R360W	T23R360W	T23R720W	T23R1K08	T23R2K88	T23R4K98
240	7.5	100%	17	T17R360W	T17R360W	T17R1K08	T17R2K16	T17R4K32	T17R6K5
240	7.5	110%	17	T17R360W	T17R360W	T17R1K08	T17R2K16	T17R4K32	T17R6K5
240	7.5	125%	17	T17R360W	T17R360W	T17R1K08	T17R2K16	T17R4K32	T17R6K5
240	7.5	150%	17	T17R360W	T17R360W	T17R1K08	T17R2K16	T17R4K32	T17R6K5
240	10	100%	11	T10R720W	T10R720W	T10R1K08	T10R2K73	T10R4K5	T10R11K0
240	10	110%	11	T10R720W	T10R720W	T10R1K08	T10R2K73	T10R4K5	T10R11K0
240	10	125%	11	T10R720W	T10R720W	T10R1K08	T10R2K73	T10R4K5	T10R11K0
240	10	150%	11	T10R720W	T10R720W	T10R1K08	T10R2K73	T10R4K5	T10R11K0

PowerFlex 40

Standard Resistors									
Input Voltage (VAC)	HP	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
480	0.5	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	0.5	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	0.5	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	0.5	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	1	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	2	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
480	2	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
480	2	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
480	2	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
480	3	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	5	100%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
480	5	110%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
480	5	125%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
480	5	150%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
480	7.5	100%	67	T67R360W	T67R360W	T67R1K08	T67R2K52	T67R3K29	T67R5K76
480	7.5	110%	67	T67R360W	T67R360W	T67R1K08	T67R2K52	T67R3K29	T67R5K76
480	7.5	125%	67	T67R360W	T67R360W	T67R1K08	T67R2K52	T67R3K29	T67R5K76
480	7.5	150%	67	T67R360W	T67R360W	T67R1K08	T67R2K52	T67R3K29	T67R5K76
480	10	100%	53	T53R360W	T53R720W	T53R1K08	T53R2K88	T53R4K8	T53R10K0
480	10	110%	53	T53R360W	T53R720W	T53R1K08	T53R2K88	T53R4K8	T53R10K0
480	10	125%	53	T53R360W	T53R720W	T53R1K08	T53R2K88	T53R4K8	T53R10K0
480	10	150%	53	T53R360W	T53R720W	T53R1K08	T53R2K88	T53R4K8	T53R10K0
480	15	100%	32	T32R360W	T32R720W	T32R2K16	T32R4K0	T32R9K51	T32R12K7
480	15	110%	32	T32R360W	T32R720W	T32R2K16	T32R4K0	T32R9K51	T32R12K7
480	15	125%	32	T32R360W	T32R720W	T32R2K16	T32R4K0	T32R9K51	T32R12K7
480	15	150%	32	T32R360W	T32R720W	T32R2K16	T32R4K0	T32R9K51	T32R12K7

PowerFlex 40

Standard Resistors									
Input Voltage (VAC)	HP	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
600	1	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	1	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	1	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	1	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	2	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
600	2	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
600	2	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
600	2	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
600	3	100%	97	T97R360W	T97R360W	T97R360W	T97R720W	T197R1K44	T97R2K88
600	3	110%	97	T97R360W	T97R360W	T97R360W	T97R720W	T197R1K44	T97R2K88
600	3	125%	97	T97R360W	T97R360W	T97R360W	T97R720W	T197R1K44	T97R2K88
600	3	150%	97	T97R360W	T97R360W	T97R360W	T97R720W	T197R1K44	T97R2K88
600	5	100%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
600	5	110%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
600	5	125%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
600	5	150%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
600	7.5	100%	60	T60R360W	T60R360W	T60R1K08	T60R2K16	T60R4K47	T60R6K85
600	7.5	110%	60	T60R360W	T60R360W	T60R1K08	T60R2K16	T60R4K47	T60R6K85
600	7.5	125%	60	T60R360W	T60R360W	T60R1K08	T60R2K16	T60R4K47	T60R6K85
600	7.5	150%	60	T60R360W	T60R360W	T60R1K08	T60R2K16	T60R4K47	T60R6K85
600	10	100%	60	T60R360W	T60R720W	T60R1K08	T60R2K16	T60R4K47	T60R9K92
600	10	110%	60	T60R360W	T60R720W	T60R1K08	T60R2K16	T60R4K47	T60R9K92
600	10	125%	60	T60R360W	T60R720W	T60R1K08	T60R2K16	T60R4K47	T60R9K92
600	10	150%	60	T60R360W	T60R720W	T60R1K08	T60R2K16	T60R4K47	T60R9K92
600	15	100%	53	T53R360W	T53R720W	T53R1K8	T53R4K8	T53R6K8	T53R12K0
600	15	110%	53	T53R360W	T53R720W	T53R1K8	T53R4K8	T53R6K8	T53R12K0
600	15	125%	53	T53R360W	T53R720W	T53R1K8	T53R4K8	T53R6K8	T53R12K0
600	15	150%	53	T53R360W	T53R720W	T53R1K8	T53R4K8	T53R6K8	T53R12K0

PowerFlex 70 & 700 Series

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
240	0.5	0.33	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	0.33	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	0.33	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	0.33	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	1	0.75	100%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	0.75	110%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	0.75	125%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	0.75	150%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	2	1.5	100%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
240	2	1.5	110%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
240	2	1.5	125%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
240	2	1.5	150%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
240	3	2	100%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	3	2	110%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	3	2	125%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	3	2	150%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	5	3	100%	32	T32R360W	T32R360W	T32R720W	T32R1K08	T32R2K88	T32R4K0
240	5	3	110%	32	T32R360W	T32R360W	T32R720W	T32R1K08	T32R2K88	T32R4K0
240	5	3	125%	32	T32R360W	T32R360W	T32R720W	T32R1K08	T32R2K88	T32R4K0
240	5	3	150%	28	T28R360W	T28R360W	T28R720W	T28R1K08	T28R2K79	T28R4K46
240	7.5	5	100%	23	T23R360W	T23R360W	T23R1K08	T23R1K8	T23R4K98	T23R6K84
240	7.5	5	110%	23	T23R360W	T23R360W	T23R1K08	T23R1K8	T23R4K98	T23R6K84
240	7.5	5	125%	23	T23R360W	T23R360W	T23R1K08	T23R1K8	T23R4K98	T23R6K84
240	10	7.5	90%	21	T21R360W	T21R720W	T21R1K08	T21R2K80	T21R4K5	T21R10K4
240	15	10	100%	11	T11R360W	T11R720W	T11R1K76	T11R3K52	T11R7K4	T11R14K1
240	15	10	110%	11	T11R360W	T11R720W	T11R1K76	T11R3K52	T11R7K4	T11R14K1
240	15	10	125%	11	T11R360W	T11R720W	T11R1K76	*	*	*
240	20	15	100%	9.3	T9F3R720W	T9F3R1K08	T9F3R2K1	T9F3R4K2	T9F3R11K0	T9F3R16K8
240	20	15	110%	9.3	T9F3R720W	T9F3R1K08	T9F3R2K1	T9F3R4K2	T9F3R11K0	T9F3R16K8
240	25	20	90%	9.3	T9F3R720W	T9F3R1K08	T9F3R2K75	T9F3R6K88	T9F3R11K0	T9F3R22K4
240	30	25	100%	7.0	T7R720W	T7R1K44	T7R4K73	T7R8K32	T7R14K9	T7R25K6
240	40	30	100%	4.8	T4F8R820W	T4F8R1K63	T4F8R4K07	T4F8R8K13	T4F8R19K2	T4F8R32K0
240	40	30	110%	4.6	T4F6R1K08	T4F6R1K80	T4F6R4K50	T4F6R15K6	*	*
240	50	40	90%	4.6	T4F6R1K08	T4F6R2K16	T4F6R6K64	T4F6R15K6	T4F6R22K4	T4F6R44K8
240	50	40	100%	4.6	T4F6R1K08	T4F6R2K16	*	*	*	*

PowerFlex 70 & 700 Series

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
240	60	50	100%	2.3	T2F3R1K38	T2F3R2K75	T2F3R6K8	T2F3R13K8	T2F3R28K8	T2F3R57K6
240	60	50	110%	2.3	T2F3R1K38	T2F3R2K75	T2F3R6K8	T2F3R13K8	T2F3R28K8	T2F3R57K6
240	60	50	125%	2.3	T2F3R1K38	T2F3R2K75	*	*	*	*
240	60	50	150%	2.3	T2F3R1K38	T2F3R2K75	*	*	*	*
240	75	60	100%	2.3	T2F3R1K69	T2F3R3K38	T2F3R13K8	T2F3R19K2	T2F3R44K8	T2F3R57K6
240	75	60	110%	2.3	T2F3R1K69	T2F3R3K38	T2F3R13K8	T2F3R19K2	T2F3R44K8	T2F3R57K6
240	75	60	125%	2.3	T2F3R1K69	T2F3R3K38	T2F3R13K8	*	*	*

PowerFlex 70 & 700 Series

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
480	0.5	0.33	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	0.5	0.33	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	0.5	0.33	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	0.5	0.33	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
480	1	0.75	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	0.75	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	0.75	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	0.75	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	2	1.5	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
480	2	1.5	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
480	2	1.5	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
480	2	1.5	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
480	3	2	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	2	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	2	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	2	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	5	3	100%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
480	5	3	110%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
480	5	3	125%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
480	5	3	150%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
480	7.5	5	100%	77	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32	T77R9K1
480	7.5	5	110%	77	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32	T77R9K1
480	7.5	5	125%	77	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32	T77R9K1
480	7.5	5	150%	67	T67R360W	T67R720W	T67R1K08	T67R1K8	T67R5K76	T67R9K26
480	10	7.5	100%	77	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32	T77R9K1
480	10	7.5	110%	77	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32	T77R9K1
480	10	7.5	125%	67	T67R360W	T67R720W	T67R1K08	T67R2K52	T67R5K76	*
480	15	10	100%	45	T45R360W	T45R720W	T45R2K16	T45R4K68	T45R11K0	T45R15K0
480	15	10	110%	45	T45R360W	T45R720W	T45R2K16	T45R4K68	T45R11K0	T45R15K0
480	15	10	125%	45	T45R360W	T45R720W	T45R2K16	T45R4K68	T45R11K0	T45R15K0
480	20	15	100%	40	T40R720W	T40R1K08	T40R2K16	T40R4K32	T40R9K92	T40R19K2
480	20	15	110%	40	T40R720W	T40R1K08	*	*	*	*
480	25	20	100%	28	T28R720W	T28R1K08	T28R2K79	T28R6K28	T28R13K0	T28R22K4
480	25	20	110%	28	T28R720W	T28R1K08	T28R2K79	T28R6K28	T28R13K0	T28R22K4
480	25	20	125%	28	T28R720W	T28R1K08	T28R2K79	*	*	*

PowerFlex 70 & 700 Series

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
480	30	25	100%	25	T25R720W	T25R1K44	T25R4K34	T25R6K25	T25R13K6	T25R25K6
480	30	25	110%	25	T25R720W	T25R1K44	T25R4K34	T25R6K25	T25R13K6	T25R25K6
480	30	25	125%	23	T23R720W	T23R1K44	T23R4K98	*	*	*
480	40	30	100%	19	T19R1K08	T19R1K87	T19R4K11	T19R8K22	T19R22K4	T19R32K0
480	40	30	110%	19	T19R1K08	T19R1K87	T19R4K11	T19R8K22	T19R22K4	T19R32K0
480	50	40	90%	19	T19R1K08	T19R2K47	T19R6K57	T19R13K6	T19R22K4	T19R44K8
480	60	50	90%	15.4	T15F4R1K44	T15F4R2K88	T15F4R6K6	T15F4R13K5	T15F4R25K6	T15F4R51K2
480	75	60	100%	9.3	T9F3R2K1	T9F3R4K2	T9F3R11K0	T9F3R16K8	T9F3R38K4	T9F3R67K2
480	75	60	110%	9.3	T9F3R2K1	T9F3R4K2	T9F3R11K0	T9F3R16K8	T9F3R38K4	T9F3R67K2
480	75	60	125%	9.3	T9F3R2K1	T9F3R4K2	T9F3R11K0	*	*	*
480	100	75	90%	9.3	T9F3R2K1	T9F3R4K2	T9F3R11K0	T9F3R22K4	T9F3R51K2	T9F3R96K0
480	125	100	100%	4.8	T4F8R2K88	T4F8R6K51	T4F8R14K0	T4F8R32K0	T4F8R57K6	T4F8R96K0
480	125	100	110%	4.8	T4F8R2K88	T4F8R6K51	T4F8R14K0	T4F8R32K0	T4F8R57K6	T4F8R96K0
480	125	100	125%	4.8	T4F8R2K88	T4F8R6K51	T4F8R14K0	*	*	*
480	150	125	100%	4.6	T4F6R3K44	T4F6R6K64	T4F6R15K6	T4F6R32K0	T4F6R64K0	T4F4R128K0
480	150	125	110%	4.6	T4F6R3K44	T4F6R6K64	T4F6R15K6	*	*	*
480	150	125	125%	4.6	T4F6R3K44	T4F6R6K64	*	*	*	*
480	200	150	100%	3.3	T3F3R4K73	T3F3R9K46	T3F3R22K4	T3F3R44K8	T3F3R86K4	T3F3R153K6
480	200	150	110%	3.3	T3F3R4K73	T3F3R9K46	T3F3R22K4	*	*	*
480	200	150	125%	3.3	T3F3R4K73	T3F3R9K46	*	*	*	*
480	250	200	100%	3.3	T3F3R6K26	T3F3R11K3	T3F3R32K0	T3F3R64K0	T3F3R115K2	T3F3R192K0
480	250	200	110%	3.3	T3F3R6K26	T3F3R11K3	*	*	*	*

PowerFlex 70 & 700 Series

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
600	0.5	0.33	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
600	0.5	0.33	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
600	0.5	0.33	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
600	0.5	0.33	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
600	1	0.75	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	1	0.75	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	1	0.75	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	1	0.75	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	2	1.5	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K44
600	2	1.5	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K44
600	2	1.5	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K44
600	2	1.5	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K44
600	3	2	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
600	3	2	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
600	3	2	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
600	3	2	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
600	5	3	100%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
600	5	3	110%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
600	5	3	125%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
600	5	3	150%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
600	7.5	5	100%	97	T97R360W	T97R360W	T97R1K08	T97R2K16	T97R4K32	T97R6K48
600	7.5	5	110%	97	T97R360W	T97R360W	T97R1K08	T97R2K16	T97R4K32	T97R6K48
600	7.5	5	125%	97	T97R360W	T97R360W	T97R1K08	T97R2K16	T97R4K32	T97R6K48
600	7.5	5	150%	97	T97R360W	T97R360W	T97R1K08	T97R2K16	T97R4K32	T97R6K48
600	10	7.5	100%	97	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32	T97R10K0
600	10	7.5	110%	97	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32	T97R10K0
600	10	7.5	125%	97	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32	T97R10K0
600	10	7.5	150%	77	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32	T77R9K1
600	15	10	100%	53	T53R360W	T53R720W	T53R1K8	T53R4K8	T53R6K8	T53R12K0
600	15	10	110%	53	T53R360W	T53R720W	T53R1K8	T53R4K8	T53R6K8	T53R12K0
600	15	10	125%	53	T53R360W	T53R720W	T53R1K8	T53R4K8	T53R6K8	T53R12K0
600	15	10	150%	53	T53R360W	T53R720W	T53R1K8	*	*	*
600	20	15	100%	45	T45R720W	T45R1K08	T45R2K16	T45R4K68	T45R11K0	T45R19K2
600	20	15	110%	45	T45R720W	T45R1K08	T45R2K16	T45R4K68	T45R11K0	T45R19K2
600	20	15	125%	45	T45R720W	T45R1K08	T45R2K16	T45R4K68	T45R11K0	T45R19K2
600	20	15	150%	45	T45R720W	T45R1K08	T45R2K16	*	*	*

PowerFlex 70 & 700 Series

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
600	25	20	100%	40	T40R720W	T40R1K08	T40R2K88	T40R5K86	T40R13K0	T40R22K4
600	25	20	110%	40	T40R720W	T40R1K08	T40R2K88	T40R5K86	T40R13K0	T40R22K4
600	25	20	125%	40	T40R720W	T40R1K08	T40R2K88	T40R5K86	T40R13K0	*
600	25	20	150%	36	T36R720W	T36R1K08	*	*	*	*
600	30	25	100%	32	T32R720W	T32R1K44	T32R4K0	T32R9K51	T32R12K7	T29R25K6
600	30	25	110%	32	T32R720W	T32R1K44	T32R4K0	T32R9K51	T32R12K7	T29R25K6
600	30	25	125%	32	T32R720W	T32R1K44	T32R4K0	T32R9K51	*	*
600	30	25	150%	29	T29R720W	T29R1K44	T29R4K4	*	*	*
600	40	30	100%	25	T25R1K08	T25R2K16	T25R4K34	T25R9K76	T25R19K2	T25R32K0
600	40	30	110%	25	T25R1K08	T25R2K16	T25R4K34	T25R9K76	T25R19K2	T25R32K0
600	40	30	125%	25	T25R1K08	T25R2K16	T25R4K34	*	*	*
600	50	40	100%	25	T25R720W	T25R2K16	T25R6K25	T25R9K76	T25R22K4	T25R44K8
600	60	50	100%	18	T18R1K8	T18R2K75	T18R6K72	T18R13K4	T18R25K6	T18R51K2
600	60	50	110%	18	T18R1K8	T18R2K75	T18R6K72	T18R13K4	T18R25K6	T18R51K2
600	60	50	125%	18	T18R1K8	T18R2K75	*	*	*	*
600	75	60	90%	18	T18R1K8	T18R3K6	T18R10K8	T18R19K2	T18R38K4	T18R64K0
600	75	60	100%	18	T18R1K8	T18R3K6	*	*	*	*
600	100	75	70%	18	T18R2K75	T18R6K72	T18R10K8	T18R25K6	T18R44K8	T18R76K8
600	125	100	100%	6.3	T6F3R2K55	T6F3R6K80	T6F3R13K6	T6F3R28K8	T6F3R57K6	T6F3R115K2
600	125	100	110%	6.3	T6F3R2K55	T6F3R6K80	T6F3R13K6	*	*	*
600	125	100	125%	6.3	T6F3R2K55	T6F3R6K80	*	*	*	*
600	150	125	100%	6.3	T6F3R4K88	T6F3R6K80	T6F3R19K2	T6F3R32K0	T6F3R67K2	T6F3R128K0
600	150	125	110%	6.3	T6F3R4K88	T6F3R6K80	T6F3R19K2	*	*	*
600	150	125	125%	6.3	T6F3R4K88	T6F3R6K80	*	*	*	*

PowerFlex 70 & 700 Series

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
690	50	40	100%	18	T18R1K08	T18R2K16	T18R6K72	T18R10K8	T18R22K4	T18R44K8
690	50	40	110%	18	T18R1K08	T18R2K16	T18R6K72	*	*	*
690	50	40	125%	18	T18R1K08	T18R2K16	T18R6K72	*	*	*
690	60	50	100%	18	T18R1K8	T18R2K75	T18R6K72	T18R19K2	T18R22K4	T18R44K8
690	60	50	110%	18	T18R1K8	T18R2K75	*	*	*	*
690	60	50	125%	18	T18R1K8	T18R2K75	*	*	*	*
690	75	60	100%	18	T18R1K8	T18R3K6	T18R10K8	T18R19K2	T18R38K4	T18R64K0
690	75	60	110%	18	T18R1K8	T18R3K6	*	*	*	*
690	75	60	125%	18	T18R1K8	T18R3K6	*	*	*	*
690	100	75	90%	18	T18R2K75	T18R6K72	T18R10K8	T18R25K6	T18R44K8	T18R76K8
690	100	75	100%	18	T18R2K75	T18R6K72	*	*	*	*
690	125	100	70%	18	T18R2K75	T18R6K72	T18R13K4	T18R28K8	T18R57K6	T18R96K0
690	125	100	80%	18	T18R2K75	T18R6K72	*	*	*	*
690	150	125	100%	7	T7R4K73	T7R8K32	T7R19K2	T7R38K4	T7R67K2	T7R134K4
690	150	125	110%	7	T7R4K73	T7R8K32	T7R19K2	T7R38K4	*	*
690	150	125	125%	7	T7R4K73	T7R8K32	T7R19K2	*	*	*
690	175	150	100%	7	T7R4K73	T7R8K32	T7R19K2	T7R38K4	T7R76K8	T7R153K6
690	175	150	110%	7	T7R4K73	T7R8K32	T7R19K2	T7R38K4	*	*
690	175	150	125%	7	T7R4K73	T7R8K32	T7R19K2	*	*	*

PowerFlex 70 & 700 Series Case Resistors

Aluminum Case Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
240	0.5	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
240	0.5	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
240	0.5	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
240	0.5	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
240	1	100%	80	TC80R200W	TC80R200W	TC80R200W	TC80R240W	*	*
240	1	110%	80	TC80R200W	TC80R200W	TC80R200W	TC80R240W	*	*
240	1	125%	80	TC80R200W	TC80R200W	TC80R200W	TC80R240W	*	*
240	1	150%	80	TC80R200W	TC80R200W	TC80R200W	TC80R240W	*	*
240	2	100%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
240	2	110%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
240	2	125%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
240	2	150%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
240	3	100%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
240	3	110%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
240	3	125%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
240	3	150%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
240	5	100%	32	TC32R200W	TC32R240W	*	*	*	*
240	5	110%	32	TC32R200W	TC32R240W	*	*	*	*
240	5	125%	32	TC32R200W	TC32R240W	*	*	*	*
240	7.5	100%	23	TC21R200W	TC21R370W	*	*	*	*
240	7.5	110%	23	TC21R200W	TC21R370W	*	*	*	*
240	10	90%	21	TC21R240W	*	*	*	*	*

PowerFlex 70 & 700 Series Case Resistors

Aluminum Case Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
480	0.5	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
480	0.5	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
480	0.5	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
480	0.5	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
480	1	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
480	1	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
480	1	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
480	1	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
480	2	100%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
480	2	110%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
480	2	125%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
480	2	150%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
480	3	100%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
480	3	110%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
480	3	125%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
480	3	150%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
480	5	100%	80	TC80R200W	TC80R240W	*	*	*	*
480	5	110%	80	TC80R200W	TC80R240W	*	*	*	*
480	5	125%	80	TC80R200W	TC80R240W	*	*	*	*
480	5	150%	80	TC80R200W	TC80R240W	*	*	*	*
480	7.5	100%	80	TC80R200W	TC80R370W	*	*	*	*
480	7.5	110%	80	TC80R200W	TC80R370W	*	*	*	*
480	7.5	125%	80	TC80R200W	TC80R370W	*	*	*	*
480	7.5	150%	68	TC80R200W	TC80R370W	*	*	*	*
480	10	100%	68	TC68R240W	*	*	*	*	*
480	10	110%	68	TC68R240W	*	*	*	*	*
480	10	125%	68	TC68R240W	*	*	*	*	*
480	15	100%	47	TC47R370W	*	*	*	*	*
480	15	110%	47	TC47R370W	*	*	*	*	*
480	15	125%	47	TC47R370W	*	*	*	*	*

PowerFlex 70 & 700 Series Case Resistors

Aluminum Case Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
600	0.5	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
600	0.5	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
600	0.5	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
600	0.5	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
600	1	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
600	1	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
600	1	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
600	1	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
600	2	100%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
600	2	110%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
600	2	125%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
600	2	150%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
600	3	100%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
600	3	110%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
600	3	125%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
600	3	150%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
600	5	100%	117	TC117R200W	TC117R240W	*	*	*	*
600	5	110%	117	TC117R200W	TC117R240W	*	*	*	*
600	5	125%	117	TC117R200W	TC117R240W	*	*	*	*
600	5	150%	117	TC117R200W	TC117R240W	*	*	*	*
600	7.5	100%	80	TC80R200W	TC80R370W	*	*	*	*
600	7.5	110%	80	TC80R200W	TC80R370W	*	*	*	*
600	7.5	125%	80	TC80R200W	TC80R370W	*	*	*	*
600	7.5	150%	80	TC80R200W	TC80R370W	*	*	*	*
600	10	100%	80	TC80R240W	*	*	*	*	*
600	10	110%	80	TC80R240W	*	*	*	*	*
600	10	125%	80	TC80R240W	*	*	*	*	*
600	10	150%	80	TC80R240W	*	*	*	*	*
600	15	100%	53	TC53R370W	*	*	*	*	*
600	15	110%	53	TC53R370W	*	*	*	*	*
600	15	125%	53	TC53R370W	*	*	*	*	*
600	15	150%	53	TC53R370W	*	*	*	*	*

PowerFlex 750

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
240	0.5	0.5	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	0.5	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	0.5	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	0.5	0.5	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
240	1	1	100%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	1	110%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	1	125%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	1	1	150%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K08
240	2	2	100%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R1K8
240	2	2	110%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R1K8
240	2	2	125%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R1K8
240	2	2	150%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R1K8
240	3	3	100%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	3	3	110%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	3	3	125%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	3	3	150%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
240	5	3	100%	23	T23R360W	T23R360W	T23R720W	T23R1K08	T23R2K16	T23R4K98
240	5	3	110%	23	T23R360W	T23R360W	T23R720W	T23R1K08	T23R2K16	T23R4K98
240	5	3	125%	23	T23R360W	T23R360W	T23R720W	T23R1K08	T23R2K16	T23R4K98
240	5	3	150%	23	T23R360W	T23R360W	T23R720W	T23R1K08	T23R2K16	T23R4K98
240	7.5	5	100%	15.4	T15F4R360W	T15F4R360W	T15F4R1K08	T15F4R2K16	T15F4R2K88	T15F4R6K6
240	7.5	5	110%	15.4	T15F4R360W	T15F4R360W	T15F4R1K08	T15F4R2K16	T15F4R2K88	T15F4R6K6
240	7.5	5	125%	15.4	T15F4R360W	T15F4R360W	T15F4R1K08	T15F4R2K16	T15F4R2K88	T15F4R6K6
240	7.5	5	150%	15.4	T15F4R360W	T15F4R360W	T15F4R1K08	T15F4R2K16	T15F4R2K88	T15F4R6K6
240	10	7.5	100%	17	T17R360W	T17R720W	T17R1K08	T17R2K16	T17R4K32	T17R10K0
240	10	7.5	110%	17	T17R360W	T17R720W	T17R1K08	T17R2K16	T17R4K32	T17R10K0
240	10	7.5	125%	16	T16R360W	T16R720W	T16R1K08	T16R2K88	T16R6K0	T16R9K
240	15	10	100%	9.3	T9F3R360W	T9F3R720W	T9F3R2K1	T9F3R4K2	T9F3R6K88	T9F3R13K5
240	15	10	110%	9.3	T9F3R360W	T9F3R720W	T9F3R2K1	T9F3R4K2	T9F3R6K88	T9F3R13K5
240	15	10	125%	9.3	T9F3R360W	T9F3R720W	T9F3R2K1	T9F3R4K2	T9F3R6K88	T9F3R13K5
240	15	10	150%	8.5	T8F5R360W	T8F5R720W	T8F5R2K0	*	*	*
240	20	15	100%	8	T8R700W	T8R1K08	T8R2K4	T8R4K8	T8R8K0	T8R19K2
240	20	15	110%	8	T8R700W	T8R1K08	T8R2K4	T8R4K8	T8R8K0	T8R19K2
240	20	15	125%	8	T8R700W	T8R1K08	T8R2K4	T8R4K8	T8R8K0	T8R19K2

PowerFlex 750

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
240	25	20	100%	4.4	T4F4R720W	T4F4R1K08	T4F4R2K75	T4F4R6K52	T4F4R10K9	T4F4R22K4
240	25	20	110%	4.4	T4F4R720W	T4F4R1K08	T4F4R2K75	T4F4R6K52	T4F4R10K9	T4F4R22K4
240	25	20	125%	4.4	T4F4R720W	T4F4R1K08	T4F4R2K75	T4F4R6K52	T4F4R10K9	*
240	25	20	150%	4.4	T4F4R720W	T4F4R1K08	*	*	*	*
240	30	25	100%	4.4	T4F4R720W	T4F4R1K44	T4F4R4K5	T4F4R6K52	T4F4R13K5	T4F4R28K8
240	30	25	110%	4.4	T4F4R720W	T4F4R1K44	T4F4R4K5	T4F4R6K52	T4F4R13K5	T4F4R28K8
240	30	25	125%	4.4	T4F4R720W	T4F4R1K44	T4F4R4K5	T4F4R6K52	*	*
240	30	25	150%	4.4	T4F4R720W	T4F4R1K44	*	*	*	*
240	40	30	100%	2.3	T2F3R1K38	T2F3R1K69	T2F3R4K5	T2F3R8K8	T2F3R17K0	T2F3R32K0
240	40	30	110%	2.3	T2F3R1K38	T2F3R1K69	T2F3R4K5	T2F3R8K8	T2F3R17K0	T2F3R32K0
240	40	30	125%	2.3	T2F3R1K38	T2F3R1K69	T2F3R4K5	T2F3R8K8	*	*
240	40	30	150%	2.3	T2F3R1K38	T2F3R1K69	*	*	*	*
240	50	40	100%	2.3	T2F3R1K38	T2F3R2K75	T2F3R6K8	T2F3R13K8	T2F3R25K6	T2F3R44K8
240	50	40	110%	2.3	T2F3R1K38	T2F3R2K75	T2F3R6K8	*	*	*
240	50	40	125%	2.3	T2F3R1K38	T2F3R2K75	*	*	*	*
240	50	40	150%	2.3	T2F3R1K38	T2F3R2K75	*	*	*	*
240	60	50	100%	2.3	T2F3R1K38	T2F3R2K75	T2F3R6K8	T2F3R13K8	T2F3R25K6	T2F3R44K8
240	60	50	110%	2.3	T2F3R1K38	T2F3R2K75	T2F3R6K8	T2F3R13K8	T2F3R25K6	T2F3R44K8
240	60	50	125%	2.3	T2F3R1K38	T2F3R2K75	*	*	*	*
240	60	50	150%	1.8	T1F8R1K62	T1F8R2K7	*	*	*	*
240	75	60	100%	1.8	T1F8R1K62	T1F8R4K5	T1F8R10K0	T1F8R19K2	T1F8R38K4	T1F8R64K0
240	75	60	110%	1.8	T1F8R1K62	T1F8R4K5	T1F8R10K0	T1F8R19K2	T1F8R38K4	T1F8R64K0
240	75	60	125%	1.8	T1F8R1K62	T1F8R4K5	T1F8R10K0	*	*	*
240	75	60	150%	1.8	T1F8R1K62	T1F8R4K5	*	*	*	*
240	100	75	100%	1.8	T1F8R2K0	T1F8R4K5	T1F8R10K0	T1F8R19K2	T1F8R44K8	T1F8R76K8
240	100	75	110%	1.8	T1F8R2K0	T1F8R4K5	T1F8R10K0	T1F8R19K2	T1F8R44K8	T1F8R76K8
240	100	75	125%	1.65	T1F65R2K16	T1F65R4K4	T1F65R11K	*	*	*
240	125	100	100%	1.2	T1F2R2K8	T1F2R5K6	T1F2R14K0	T1F2R28K8	T1F2R57K6	T1F2R96K0
240	125	100	110%	1.2	T1F2R2K8	T1F2R5K6	T1F2R14K0	T1F2R28K8	T1F2R57K6	T1F2R96K0
240	125	100	125%	1.2	T1F2R2K8	T1F2R5K6	*	*	*	*
240	150	125	100%	0.82	T0F82R3K3	T0F82R6K7	T0F82R22K4	T0F82R32K0	T0F82R67K2	T0F82R128K0
240	150	125	110%	0.82	T0F82R3K3	T0F82R6K7	T0F82R22K4	*	*	*
240	150	125	125%	0.82	T0F82R3K3	T0F82R6K7	*	*	*	*
240	150	125	150%	0.82	T0F82R3K3	T0F82R6K7	*	*	*	*
240	200	150	100%	0.82	T0F82R4K5	T0F82R9K0	T0F82R22K4	T0F82R44K8	T0F82R86K4	T0F82R153K6
240	200	150	110%	0.82	T0F82R4K5	T0F82R9K0	T0F82R22K4	*	*	*
240	200	150	125%	0.82	T0F82R4K5	T0F82R9K0	*	*	*	*

PowerFlex 750

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
480	1	1	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	1	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	1	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	1	1	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
480	2	2	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
480	2	2	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
480	2	2	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
480	2	2	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
480	3	3	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	3	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	3	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	3	3	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
480	5	5	100%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
480	5	5	110%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
480	5	5	125%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
480	5	5	150%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
480	7.5	7.5	100%	60	T60R360W	T60R360W	T60R1K08	T60R2K16	T60R4K47	T60R6K85
480	7.5	7.5	110%	60	T60R360W	T60R360W	T60R1K08	T60R2K16	T60R4K47	T60R6K85
480	7.5	7.5	125%	60	T60R360W	T60R360W	T60R1K08	T60R2K16	T60R4K47	T60R6K85
480	7.5	7.5	150%	60	T60R360W	T60R360W	T60R1K08	T60R2K16	T60R4K47	T60R6K85
480	10	7.5	100%	40	T40R360W	T40R720W	T40R1K08	T40R2K16	T40R4K32	T40R9K92
480	10	7.5	110%	40	T40R360W	T40R720W	T40R1K08	T40R2K16	T40R4K32	T40R9K92
480	10	7.5	125%	40	T40R360W	T40R720W	T40R1K08	T40R2K16	T40R4K32	T40R9K92
480	10	7.5	150%	40	T40R360W	T40R720W	T40R1K08	*	*	*
480	15	10	100%	32	T32R360W	T32R720W	T32R2K16	T32R4K0	T32R6K5	T32R12K7
480	15	10	110%	32	T32R360W	T32R720W	T32R2K16	T32R4K0	T32R6K5	T32R12K7
480	15	10	125%	32	T32R360W	T32R720W	T32R2K16	T32R4K0	T32R6K5	T32R12K7
480	15	10	150%	32	T32R360W	T32R720W	T32R2K16	*	*	*
480	20	15	100%	32	T32R720W	T32R1K08	T32R2K88	T32R5K6	T32R9K51	T32R19K2
480	20	15	110%	32	T32R720W	T32R1K08	T32R2K88	T32R5K6	T32R9K51	T32R19K2
480	20	15	125%	32	T32R720W	T32R1K08	T32R2K88	T32R5K6	T32R9K51	T32R19K2
480	25	20	100%	32	T32R720W	T32R1K08	T32R2K88	T32R5K6	T32R12K7	T32R19K2
480	25	20	110%	32	T32R720W	T32R1K08	T32R2K88	*	*	*

PowerFlex 750

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
480	30	25	100%	19	T19R720W	T19R1K44	T19R4K11	T19R6K57	T19R13K6	T19R25K6
480	30	25	110%	19	T19R720W	T19R1K44	T19R4K11	T19R6K57	T19R13K6	T19R25K6
480	30	25	125%	19	T19R720W	T19R1K44	T19R4K11	T19R6K57	*	*
480	30	25	150%	19	T19R720W	T19R1K44	*	*	*	*
480	40	30	100%	16	T16R1K08	T16R2K16	T16R6K0	T16R9K0	T16R19K2	T16R32K0
480	40	30	110%	16	T16R1K08	T16R2K16	T16R6K0	T16R9K0	T16R19K2	T16R32K0
480	40	30	125%	16	T16R1K08	T16R2K16	T16R6K0	T16R9K0	*	*
480	50	40	100%	16	T16R1K08	T16R2K88	T16R6K0	T16R11K5	T16R22K4	T16R44K8
480	50	40	110%	16	T16R1K08	T16R2K88	T16R6K0	*	*	*
480	60	50	100%	8	T8R1K44	T8R2K4	T8R6K6	T8R13K6	T8R28K8	T8R51K2
480	60	50	110%	8	T8R1K44	T8R2K4	T8R6K6	T8R13K6	T8R28K8	T8R51K2
480	60	50	125%	8	T8R1K44	T8R2K4	T8R6K6	T8R13K6	*	*
480	60	50	150%	8	T8R1K44	T8R2K4	*	*	*	*
480	75	60	100%	8	T8R1K80	T8R4K8	T8R8K0	T8R19K2	T8R38K4	T8R64K0
480	75	60	110%	8	T8R1K80	T8R4K8	T8R8K0	T8R19K2	T8R38K4	T8R64K0
480	75	60	125%	8	T8R1K80	T8R4K8	T8R8K0	*	*	*
480	100	75	100%	4.4	T4F4R2K75	T4F4R4K5	T4F4R13K5	T4F4R22K4	T4F4R44K8	T4F4R86K4
480	100	75	110%	4.4	T4F4R2K75	T4F4R4K5	T4F4R13K5	*	*	*
480	100	75	125%	4.4	T4F4R2K75	T4F4R4K5	*	*	*	*
480	125	100	100%	4.4	T4F4R2K75	T4F4R6K52	T4F4R13K5	T4F4R28K8	T4F4R57K6	T4F4R96K0
480	125	100	110%	4.4	T4F4R2K75	T4F4R6K52	T4F4R13K5	*	*	*
480	125	100	125%	4.4	T4F4R2K75	T4F4R6K52	*	*	*	*
480	150	125	100%	3.5	T3F5R3K4	T3F5R8K6	T3F5R22K4	T3F5R44K8	T3F5R64K0	T3F5R128K0
480	150	125	110%	3.5	T3F5R3K4	T3F5R8K6	T3F5R22K4	*	*	*
480	150	125	125%	3.5	T3F5R3K4	T3F5R8K6	*	*	*	*
480	200	150	100%	3.5	T3F5R4K5	T3F5R8K6	T3F5R22K4	T3F5R44K8	T3F5R86K4	T3F5R153K6
480	200	150	110%	3.5	T3F5R4K5	T3F5R8K6	T3F5R22K4	*	*	*
480	200	150	125%	3.3	T3F3R4K73	T3F3R9K46	*	*	*	*
480	250	200	100%	2.4	T2F4R6K8	T2F4R13K6	T2F4R28K8	T2F4R57K6	T2F4R96K0	T2F4R192K0
480	250	200	110%	2.4	T2F4R6K8	T2F4R13K6	T2F4R28K8	*	*	*
480	250	200	125%	2.4	T2F4R6K8	T2F4R13K6	*	*	*	*
480	300	250	100%	2.4	T2F4R6K8	T2F4R13K6	T2F4R28K8	T2F4R57K6	T2F4R128K0	T2F4R230K4
480	300	250	110%	2.4	T2F4R6K8	T2F4R13K6	*	*	*	*
480	300	250	125%	2.3	T2F3R6K8	T2F3R19K2	*	*	*	*
480	350	300	100%	1.8	T1F8R10K0	T1F8R19K2	T1F8R38K4	T1F8R76K8	T1F8R144K0	T1F8R288K0
480	350	300	110%	1.8	T1F8R10K0	T1F8R19K2	*	*	*	*
480	350	300	125%	1.8	T1F8R10K0	*	*	*	*	*

PowerFlex 750

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
600	1	1	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	1	1	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	1	1	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	1	1	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
600	2	1	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
600	2	1	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
600	2	1	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
600	2	1	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16
600	3	2	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
600	3	2	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
600	3	2	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
600	3	2	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
600	5	3	100%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
600	5	3	110%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
600	5	3	125%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
600	5	3	150%	77	T77R360W	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32
600	7.5	5	100%	77	T77R360W	T77R360W	T77R1K08	T77R2K16	T77R4K32	T77R5K7
600	7.5	5	110%	77	T77R360W	T77R360W	T77R1K08	T77R2K16	T77R4K32	T77R5K7
600	7.5	5	125%	77	T77R360W	T77R360W	T77R1K08	T77R2K16	T77R4K32	T77R5K7
600	7.5	5	150%	77	T77R360W	T77R360W	T77R1K08	T77R2K16	T77R4K32	T77R5K7
600	10	7.5	100%	60	T60R360W	T60R720W	T60R1K08	T60R2K16	T60R4K47	T60R10K0
600	10	7.5	110%	60	T60R360W	T60R720W	T60R1K08	T60R2K16	T60R4K47	T60R10K0
600	10	7.5	125%	60	T60R360W	T60R720W	T60R1K08	T60R2K16	T60R4K47	T60R10K0
600	10	7.5	150%	60	T60R360W	T60R720W	T60R1K08	T60R2K16	T60R4K47	T60R10K0
600	15	10	100%	40	T40R360W	T40R720W	T40R2K16	T40R3K96	T40R6K85	T40R13K0
600	15	10	110%	40	T40R360W	T40R720W	T40R2K16	T40R3K96	T40R6K85	T40R13K0
600	15	10	125%	40	T40R360W	T40R720W	T40R2K16	T40R3K96	T40R6K85	T40R13K0
600	15	10	150%	40	T40R360W	T40R720W	T40R2K16	*	*	*
600	20	15	100%	40	T40R720W	T40R1K08	T40R2K16	T40R4K32	T40R10K2	T40R19K2
600	20	15	110%	40	T40R720W	T40R1K08	T40R2K16	T40R4K32	T40R10K2	T40R19K2
600	20	15	125%	40	T40R720W	T40R1K08	T40R2K16	T40R4K32	T40R10K2	T40R19K2
600	20	15	150%	40	T40R720W	T40R1K08	*	*	*	*
600	25	20	100%	36	T36R720W	T36R1K44	T36R2K88	T36R5K72	T36R11K3	T36R25K6
600	25	20	110%	36	T36R720W	T36R1K44	T36R2K88	T36R5K72	T36R11K3	T36R25K6
600	25	20	125%	36	T36R720W	T36R1K44	T36R2K88	T36R5K72	T36R11K3	*
600	25	20	150%	32	T32R720W	T32R1K44	T32R2K88	*	*	*

PowerFlex 750

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
600	30	25	100%	32	T32R720W	T32R1K44	T32R4K0	T32R9K51	T32R12K7	T32R25K6
600	30	25	110%	32	T32R720W	T32R1K44	T32R4K0	T32R9K51	T32R12K7	T32R25K6
600	30	25	125%	32	T32R720W	T32R1K44	T32R4K0	T32R9K51	*	*
600	40	30	100%	17	T17R1K08	T17R2K16	T17R5K05	T17R10K0	T17R19K2	T17R32K0
600	40	30	110%	17	T17R1K08	T17R2K16	T17R5K05	T17R10K0	T17R19K2	T17R32K0
600	40	30	125%	17	T17R1K08	T17R2K16	T17R5K05	T17R10K0	*	*
600	40	30	150%	17	T17R1K08	T17R2K16	*	*	*	*
600	50	40	100%	15.4	T15F4R1K44	T15F4R2K16	T15F4R6K6	T15F4R13K5	T15F4R25K6	T15F4R44K8
600	50	40	110%	15.4	T15F4R1K44	T15F4R2K16	T15F4R6K6	T15F4R13K5	T15F4R25K6	T15F4R44K8
600	50	40	125%	15.4	T15F4R1K44	T15F4R2K16	*	*	*	*

PowerFlex 750

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
690	10	7.5	100%	60	T60R360W	T60R720W	T60R1K08	T60R2K16	T60R4K47	T60R10K0
690	10	7.5	110%	60	T60R360W	T60R720W	T60R1K08	T60R2K16	T60R4K47	T60R10K0
690	10	7.5	125%	60	T60R360W	T60R720W	T60R1K08	T60R2K16	T60R4K47	T60R10K0
690	10	7.5	150%	60	T60R360W	T60R720W	*	*	*	*
690	15	10	100%	40	T40R360W	T40R720W	T40R1K44	T40R3K96	T40R6K85	T40R13K0
690	15	10	110%	40	T40R360W	T40R720W	T40R1K44	T40R3K96	T40R6K85	T40R13K0
690	15	10	125%	40	T40R360W	T40R720W	T40R1K44	T40R3K96	T40R6K85	T40R13K0
690	15	10	150%	40	T40R360W	T40R720W	*	*	*	*
690	20	15	100%	32	T32R720W	T32R1K08	T32R2K88	T32R5K6	T32R9K51	T32R19K2
690	20	15	110%	32	T32R720W	T32R1K08	T32R2K88	T32R5K6	T32R9K51	T32R19K2
690	20	15	125%	32	T32R720W	T32R1K08	T32R2K88	T32R5K6	T32R9K51	*
690	20	15	150%	32	T32R720W	T32R1K08	*	*	*	*
690	25	20	100%	25	T25R720W	T25R1K08	T25R2K7	T25R6K25	T25R13K6	T25R22K4
690	25	20	110%	25	T25R720W	T25R1K08	T25R2K7	T25R6K25	T25R13K6	T25R22K4
690	25	20	125%	25	T25R720W	T25R1K08	T25R2K7	T25R6K25	*	*
690	25	20	150%	25	T25R720W	T25R1K08	T25R2K7	*	*	*
690	30	25	100%	25	T25R720W	T25R1K44	T25R4K34	T25R6K25	T25R13K6	T25R25K6
690	30	25	110%	25	T25R720W	T25R1K44	T25R4K34	T25R6K25	T25R13K6	T25R25K6
690	30	25	125%	25	T25R720W	T25R1K44	T25R4K34	T25R6K25	*	*
690	30	25	150%	25	T25R720W	T25R1K44	*	*	*	*
690	40	30	100%	17	T17R1K08	T17R2K16	T17R5K05	T17R10K0	T17R19K2	T17R32K0
690	40	30	110%	17	T17R1K08	T17R2K16	T17R5K05	T17R10K0	T17R19K2	T17R32K0
690	40	30	125%	17	T17R1K08	T17R2K16	T17R5K05	T17R10K0	*	*
690	40	30	150%	17	T17R1K08	T17R2K16	*	*	*	*
690	50	40	100%	17	T17R1K08	T17R2K88	T17R6K5	T17R11K2	T17R22K4	T17R44K8
690	50	40	110%	17	T17R1K08	T17R2K88	T17R6K5	T17R11K2	T17R22K4	T17R44K8
690	50	40	125%	17	T17R1K08	T17R2K88	*	*	*	*
690	50	40	150%	15	T15R2K08	T15R4K17	*	*	*	*
690	60	50	100%	10	T10R1K37	T10R2K73	T10R11K0	T10R14K1	T10R28K8	T10R51K2
690	60	50	110%	10	T10R1K37	T10R2K73	T10R11K0	T10R14K1	T10R28K8	T10R51K2
690	60	50	125%	10	T10R1K37	T10R2K73	*	*	*	*
690	60	50	150%	11	T10R2K73	T10R5K29	*	*	*	*
690	75	60	100%	10	T10R1K88	T10R4K5	T10R11K0	T10R19K2	T10R38K4	T10R67K2
690	75	60	110%	10	T10R1K88	T10R4K5	T10R11K0	T10R19K2	T10R38K4	T10R67K2
690	75	60	125%	10	T10R1K88	T10R4K5	*	*	*	*

PowerFlex 750

Standard Resistors										
Input Voltage (VAC)	HP (Normal Duty)	HP (Heavy Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
					5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
690	100	75	100%	7	T7R2K23	T7R4K73	T7R14K9	T7R25K6	T7R51K2	T7R96K0
690	100	75	110%	7	T7R2K23	T7R4K73	T7R14K9	*	*	*
690	100	75	125%	7	T7R2K23	T7R4K73	*	*	*	*
690	125	100	100%	7	T7R4K73	T7R5K58	T7R14K9	T7R28K8	T7R57K6	T7R96K0
690	125	100	110%	7	T7R4K73	T7R5K58	T7R14K9	*	*	*
690	125	100	125%	7	T7R4K73	T7R5K58	*	*	*	*
690	150	125	100%	7	T7R4K73	T7R8K32	T7R19K2	T7R38K4	T7R67K2	T7R115K2
690	150	125	110%	7	T7R4K73	T7R8K32	T7R19K2	*	*	*
690	150	125	125%	7	T7R4K73	T7R8K32	*	*	*	*
690	200	150	100%	4.4	T4F4R4K5	T4F4R10K9	T4F4R22K4	T4F4R44K8	T4F4R86K4	T4F4R163K2
690	200	150	110%	4.4	T4F4R4K5	T4F4R10K9	T4F4R22K4	*	*	*
690	200	150	125%	4.4	T4F4R4K5	T4F4R10K9	*	*	*	*
690	250	200	100%	4.4	T4F4R6K52	T4F4R13K5	T4F4R28K8	T4F4R57K6	T4F4R115K2	T4F4R201K6
690	250	200	110%	4.4	T4F4R6K52	T4F4R13K5	*	*	*	*
690	250	200	125%	4.4	T4F4R6K52	T4F4R13K5	*	*	*	*
690	300	250	100%	3.3	T3F3R6K26	T3F3R11K3	T3F3R32K0	T3F3R64K0	T3F3R128K0	T3F3R259K2
690	300	250	110%	3.3	T3F3R6K26	T3F3R11K3	T3F3R32K0	*	*	*
690	300	250	125%	3.3	T3F3R6K26	T3F3R11K3	*	*	*	*

PowerFlex 750 Case Resistors

Aluminum Case Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
240	0.5	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
240	0.5	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
240	0.5	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
240	0.5	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
240	1	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
240	1	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
240	1	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
240	1	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
240	2	100%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
240	2	110%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
240	2	125%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
240	2	150%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
240	3	100%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
240	3	110%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
240	3	125%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
240	3	150%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
240	5	100%	27	TC27R200W	TC27R240W	*	*	*	*
240	5	110%	27	TC27R200W	TC27R240W	*	*	*	*
240	5	125%	27	TC27R200W	TC27R240W	*	*	*	*
240	5	150%	27	TC27R200W	TC27R240W	*	*	*	*
240	7.5	100%	18	TC18R200W	TC18R370W	*	*	*	*
240	7.5	110%	18	TC18R200W	TC18R370W	*	*	*	*
240	7.5	125%	18	TC18R200W	TC18R370W	*	*	*	*
240	7.5	150%	18	TC18R200W	TC18R370W	*	*	*	*
240	10	100%	16	TC15R240W	*	*	*	*	*
240	10	110%	16	TC15R240W	*	*	*	*	*
240	10	125%	16	TC15R240W	*	*	*	*	*

PowerFlex 750 Case Resistors

Aluminum Case Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
480	1	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
480	1	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
480	1	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
480	1	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
480	2	100%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
480	2	110%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
480	2	125%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
480	2	150%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
480	3	100%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
480	3	110%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
480	3	125%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
480	3	150%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
480	5	100%	80	TC80R200W	TC80R240W	*	*	*	*
480	5	110%	80	TC80R200W	TC80R240W	*	*	*	*
480	5	125%	80	TC80R200W	TC80R240W	*	*	*	*
480	5	150%	80	TC80R200W	TC80R240W	*	*	*	*
480	7.5	100%	68	TC68R200W	*	*	*	*	*
480	7.5	110%	68	TC68R200W	*	*	*	*	*
480	7.5	125%	68	TC68R200W	*	*	*	*	*
480	7.5	150%	68	TC68R200W	*	*	*	*	*
480	10	100%	47	TC47R240W	*	*	*	*	*
480	10	110%	47	TC47R240W	*	*	*	*	*
480	10	125%	47	TC47R240W	*	*	*	*	*
480	10	150%	47	TC47R240W	*	*	*	*	*
480	15	100%	27	TC27R370W	*	*	*	*	*
480	15	110%	27	TC27R370W	*	*	*	*	*
480	15	125%	27	TC27R370W	*	*	*	*	*
480	15	150%	27	TC27R370W	*	*	*	*	*

PowerFlex 750 Case Resistors

Aluminum Case Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
600	1	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
600	1	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
600	1	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
600	1	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
600	2	100%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
600	2	110%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
600	2	125%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
600	2	150%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
600	3	100%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
600	3	110%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
600	3	125%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
600	3	150%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
600	5	100%	117	TC117R200W	TC117R240W	*	*	*	*
600	5	110%	117	TC117R200W	TC117R240W	*	*	*	*
600	5	125%	117	TC117R200W	TC117R240W	*	*	*	*
600	5	150%	117	TC117R200W	TC117R240W	*	*	*	*
600	7.5	100%	80	TC80R200W	TC80R370W	*	*	*	*
600	7.5	110%	80	TC80R200W	TC80R370W	*	*	*	*
600	7.5	125%	80	TC80R200W	TC80R370W	*	*	*	*
600	7.5	150%	80	TC80R200W	TC80R370W	*	*	*	*
600	10	100%	47	TC47R240W	*	*	*	*	*
600	10	110%	47	TC47R240W	*	*	*	*	*
600	10	125%	47	TC47R240W	*	*	*	*	*
600	10	150%	47	TC47R240W	*	*	*	*	*
600	15	100%	47	TC47R370W	*	*	*	*	*
600	15	110%	47	TC47R370W	*	*	*	*	*
600	15	125%	47	TC47R370W	*	*	*	*	*
600	15	150%	47	TC47R370W	*	*	*	*	*
690	10	100%	47	TC47R240W	*	*	*	*	*
690	10	110%	47	TC47R240W	*	*	*	*	*
690	10	125%	47	TC47R240W	*	*	*	*	*
690	10	150%	47	TC47R240W	*	*	*	*	*
690	15	100%	47	TC47R370W	*	*	*	*	*
690	15	110%	47	TC47R370W	*	*	*	*	*
690	15	125%	47	TC47R370W	*	*	*	*	*
690	15	150%	47	TC47R370W	*	*	*	*	*

PowerFlex 520

Standard Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
100-120V 1-phase	0.25	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.25	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.25	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.25	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.5	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	1	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1.5	100%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K44
	1.5	110%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K44
	1.5	125%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K44
	1.5	150%	77	T77R360W	T77R360W	T77R360W	T77R360W	T77R720W	T77R1K44
200-240V 1-phase	0.25	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.25	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.25	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.25	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.5	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	1	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R720W
	1	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R720W
	1	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R720W
	1	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R720W
	2	100%	67	T67R360W	T67R360W	T67R360W	T67R720W	T67R1K08	T67R1K8
	2	110%	67	T67R360W	T67R360W	T67R360W	T67R720W	T67R1K08	T67R1K8
	2	125%	67	T67R360W	T67R360W	T67R360W	T67R720W	T67R1K08	T67R1K8
	2	150%	67	T67R360W	T67R360W	T67R360W	T67R720W	T67R1K08	T67R1K8
	3	100%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
	3	110%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
	3	125%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88
	3	150%	40	T40R360W	T40R360W	T40R360W	T40R720W	T40R1K44	T40R2K88

PowerFlex 520

Standard Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
200-240V 3-phase	0.25	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.25	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.25	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.25	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W
	0.5	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	1	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	2	100%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
	2	110%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
	2	125%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
	2	150%	60	T60R360W	T60R360W	T60R360W	T60R720W	T60R1K08	T60R2K16
	3	100%	36	T36R360W	T36R360W	T36R360W	T36R720W	T36R1K44	T36R2K88
	3	110%	36	T36R360W	T36R360W	T36R360W	T36R720W	T36R1K44	T36R2K88
	3	125%	36	T36R360W	T36R360W	T36R360W	T36R720W	T36R1K44	T36R2K88
	3	150%	36	T36R360W	T36R360W	T36R360W	T36R720W	T36R1K44	T36R2K88
	5	100%	25	T25R360W	T25R360W	T25R720W	T25R1K08	T25R2K16	T25R4K34
	5	110%	25	T25R360W	T25R360W	T25R720W	T25R1K08	T25R2K16	T25R4K34
	5	125%	25	T25R360W	T25R360W	T25R720W	T25R1K08	T25R2K16	T25R4K34
	5	150%	25	T25R360W	T25R360W	T25R720W	T25R1K08	T25R2K16	T25R4K34
	7.5	100%	17	T17R360W	T17R360W	T17R720W	T17R1K5	T17R4K32	T17R6K5
	7.5	110%	17	T17R360W	T17R360W	T17R720W	T17R1K5	T17R4K32	T17R6K5
	7.5	125%	17	T17R360W	T17R360W	T17R720W	T17R1K5	T17R4K32	T17R6K5
	7.5	150%	17	T17R360W	T17R360W	T17R720W	T17R1K5	T17R4K32	T17R6K5
	10	100%	15.4	T15F4R360W	T15F4R720W	T15F4R1K44	T15F4R2K88	T15F4R6K6	T15F4R13K5
	10	110%	15.4	T15F4R360W	T15F4R720W	T15F4R1K44	T15F4R2K88	T15F4R6K6	T15F4R13K5
	10	125%	15.4	T15F4R360W	T15F4R720W	T15F4R1K44	T15F4R2K88	T15F4R6K6	T15F4R13K5
	10	150%	14	T14R360W	T14R720W	T14R1K08	T14R1K95	*	*
	15	100%	14	T14R360W	T14R720W	T14R1K95	T14R4K8	T14R6K8	T14R12K6
	20	100%	10	T10R720W	T10R1K08	T10R2K73	T10R4K5	T10R11K0	T10R19K2
	20	110%	10	T10R720W	T10R1K08	*	*	*	*

PowerFlex 520

Standard Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
380-480V 3-phase	0.5	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	1	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	2	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
	2	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
	2	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
	2	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
	3	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
	3	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
	3	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
	3	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
	5	100%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
	5	110%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
	5	125%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
	5	150%	97	T97R360W	T97R360W	T97R720W	T97R1K08	T97R2K16	T97R4K32
	7.5	100%	53	T53R360W	T53R360W	T53R1K08	T53R1K8	T53R4K8	T53R6K8
	7.5	110%	53	T53R360W	T53R360W	T53R1K08	T53R1K8	T53R4K8	T53R6K8
	7.5	125%	53	T53R360W	T53R360W	T53R1K08	T53R1K8	T53R4K8	T53R6K8
	7.5	150%	53	T53R360W	T53R360W	T53R1K08	T53R1K8	T53R4K8	T53R6K8
	10	100%	53	T53R360W	T53R720W	T53R1K08	T53R2K16	T53R4K8	T53R10K0
	10	110%	53	T53R360W	T53R720W	T53R1K08	T53R2K16	T53R4K8	T53R10K0
	10	125%	53	T53R360W	T53R720W	T53R1K08	T53R2K16	T53R4K8	T53R10K0
	10	150%	53	T53R360W	T53R720W	T53R1K08	T53R2K16	T53R4K8	T53R10K0
	15	100%	45	T45R360W	T45R720W	T45R2K16	T45R4K68	T45R6K0	T45R13K3
	15	110%	45	T45R360W	T45R720W	T45R2K16	T45R4K68	T45R6K0	T45R13K3
	15	125%	45	T45R360W	T45R720W	T45R2K16	*	*	*
	20	95%	43	T43R720W	T43R1K44	T43R3K92	T43R5K11	T43R11K0	T43R19K2
	20	100%	43	T43R720W	T43R1K44	T43R3K92	*	*	*
	25	100%	28	T28R720W	T28R1K08	T28R2K79	T28R6K28	T28R10K1	T28R22K4
	25	110%	28	T28R720W	T28R1K08	T28R2K79	T28R6K28	T28R10K1	T28R22K4
	25	125%	28	T28R720W	T28R1K08	*	*	*	*
	30	100%	28	T28R720W	T28R1K44	T28R4K46	T28R6K28	T28R13K0	T28R25K6

PowerFlex 520

Standard Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
525-600V 3-phase	0.5	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	0.5	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W
	1	100%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	110%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	125%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	1	150%	121	T121R360W	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08
	2	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
	2	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
	2	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
	2	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K08	T121R1K8
	3	100%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
	3	110%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
	3	125%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
	3	150%	121	T121R360W	T121R360W	T121R360W	T121R720W	T121R1K44	T121R2K52
	5	100%	121	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16	T121R5K61
	5	110%	121	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16	T121R5K61
	5	125%	121	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16	T121R5K61
	5	150%	121	T121R360W	T121R360W	T121R720W	T121R1K08	T121R2K16	T121R5K61
	7.5	100%	97	T97R360W	T97R360W	T97R1K08	T97R1K8	T97R4K32	T97R6K48
	7.5	110%	97	T97R360W	T97R360W	T97R1K08	T97R1K8	T97R4K32	T97R6K48
	7.5	125%	97	T97R360W	T97R360W	T97R1K08	T97R1K8	T97R4K32	T97R6K48
	7.5	150%	97	T97R360W	T97R360W	T97R1K08	T97R1K8	T97R4K32	T97R6K48
	10	100%	77	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32	T77R9K1
	10	110%	77	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32	T77R9K1
	10	125%	77	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32	T77R9K1
	10	150%	77	T77R360W	T77R720W	T77R1K08	T77R2K16	T77R4K32	T77R9K1
	15	100%	67	T67R360W	T67R720W	T67R1K8	T67R3K29	T67R9K26	T67R13K0
	15	110%	67	T67R360W	T67R720W	T67R1K8	T67R3K29	T67R9K26	T67R13K0
	15	125%	67	T67R360W	T67R720W	T67R1K8	T67R3K29	T67R9K26	T67R13K0
	15	150%	60	T60R360W	T60R720W	T60R1K8	*	*	*
	20	100%	60	T60R720W	T60R1K44	T60R2K52	T60R5K5	T60R10K0	T60R19K2
	20	110%	60	T60R720W	T60R1K44	T60R2K52	T60R5K5	*	*
	25	95%	53	T53R720W	T53R1K08	T53R2K88	T53R6K8	T53R10K0	T53R19K2
	25	100%	53	T53R720W	T53R1K08	T53R2K88	T53R6K8	*	*
	30	100%	36	T36R720W	T36R1K44	T36R4K63	T36R11K3	T36R19K2	T36R25K6
	30	110%	36	T36R720W	T36R1K44	T36R4K63	T36R11K3	T36R19K2	T36R25K6
	30	125%	34	T34R720W	T34R1K44	T34R3K6	T34R6K8	*	*

PowerFlex 520 Case Resistors

Aluminum Case Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
100-120V 1-phase	0.25	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.25	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.25	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.25	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.5	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	1	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1.5	100%	80	TC80R200W	TC80R200W	TC80R200W	TC80R370W	*	*
	1.5	110%	80	TC80R200W	TC80R200W	TC80R200W	TC80R370W	*	*
	1.5	125%	80	TC80R200W	TC80R200W	TC80R200W	TC80R370W	*	*
	1.5	150%	80	TC80R200W	TC80R200W	TC80R200W	TC80R370W	*	*
200-240V 1-phase	0.25	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.25	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.25	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.25	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.5	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	1	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	2	100%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
	2	110%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
	2	125%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
	2	150%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
	3	100%	36	TC36R200W	TC36R200W	TC36R370W	*	*	*
	3	110%	36	TC36R200W	TC36R200W	TC36R370W	*	*	*
	3	125%	36	TC36R200W	TC36R200W	TC36R370W	*	*	*
	3	150%	36	TC36R200W	TC36R200W	TC36R370W	*	*	*

PowerFlex 520 Case Resistors

Aluminum Case Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
200-240V 3-phase	0.25	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.25	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.25	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.25	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W
	0.5	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	1	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	2	100%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
	2	110%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
	2	125%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
	2	150%	47	TC47R200W	TC47R200W	TC47R240W	*	*	*
	3	100%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
	3	110%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
	3	125%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
	3	150%	39	TC39R200W	TC39R200W	TC39R370W	*	*	*
	5	100%	27	TC27R200W	TC27R240W	*	*	*	*
	5	110%	27	TC27R200W	TC27R240W	*	*	*	*
	5	125%	27	TC27R200W	TC27R240W	*	*	*	*
	5	150%	27	TC27R200W	TC27R240W	*	*	*	*
	7.5	100%	18	TC18R200W	TC18R370W	*	*	*	*
	7.5	110%	18	TC18R200W	TC18R370W	*	*	*	*
	7.5	125%	18	TC18R200W	TC18R370W	*	*	*	*
	7.5	150%	18	TC18R200W	TC18R370W	*	*	*	*
	10	100%	15	TC15R240W	*	*	*	*	*
	10	110%	15	TC15R240W	*	*	*	*	*
	10	125%	15	TC15R240W	*	*	*	*	*
	10	150%	15	TC15R240W	*	*	*	*	*

PowerFlex 520 Case Resistors

Aluminum Case Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
380-480V 3-phase	0.5	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	1	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	2	100%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
	2	110%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
	2	125%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
	2	150%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
	3	100%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
	3	110%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
	3	125%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
	3	150%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
	5	100%	80	TC80R200W	TC80R240W	*	*	*	*
	5	110%	80	TC80R200W	TC80R240W	*	*	*	*
	5	125%	80	TC80R200W	TC80R240W	*	*	*	*
	5	150%	80	TC80R200W	TC80R240W	*	*	*	*
	7.5	100%	68	TC68R200W	TC68R370W	*	*	*	*
	7.5	110%	68	TC68R200W	TC68R370W	*	*	*	*
	7.5	125%	68	TC68R200W	TC68R370W	*	*	*	*
	7.5	150%	68	TC68R200W	TC68R370W	*	*	*	*
	10	100%	53	TC53R300W	*	*	*	*	*
	10	110%	53	TC53R300W	*	*	*	*	*
	10	125%	53	TC53R300W	*	*	*	*	*
	10	150%	53	TC53R300W	*	*	*	*	*

PowerFlex 520 Case Resistors

Aluminum Case Resistors									
Input Voltage (VAC)	HP (Normal Duty)	Braking Torque	Rated Resistor Ohms	Part Number					
				5% Braking E-Stop	10% Braking 5% OHL	25% Braking 12.5% OHL	50% Braking 25% OHL	50% OHL	100% OHL
525-600V 3-phase	0.5	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	0.5	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*
	1	100%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	110%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	125%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	1	150%	117	TC117R200W	TC117R200W	TC117R200W	TC117R240W	*	*
	2	100%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
	2	110%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
	2	125%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
	2	150%	117	TC117R200W	TC117R200W	TC117R240W	*	*	*
	3	100%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
	3	110%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
	3	125%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
	3	150%	117	TC117R200W	TC117R200W	TC117R370W	*	*	*
	5	100%	117	TC117R200W	TC117R240W	*	*	*	*
	5	110%	117	TC117R200W	TC117R240W	*	*	*	*
	5	125%	117	TC117R200W	TC117R240W	*	*	*	*
	5	150%	117	TC117R200W	TC117R240W	*	*	*	*
	7.5	100%	80	TC80R200W	TC80R370W	*	*	*	*
	7.5	110%	80	TC80R200W	TC80R370W	*	*	*	*
	7.5	125%	80	TC80R200W	TC80R370W	*	*	*	*
	7.5	150%	80	TC80R200W	TC80R370W	*	*	*	*
	10	100%	80	TC80R240W	*	*	*	*	*
	10	110%	80	TC80R240W	*	*	*	*	*
	10	125%	80	TC80R240W	*	*	*	*	*
	10	150%	80	TC80R240W	*	*	*	*	*

Standard Resistors

Part Number	Resistance (Ohms)	Power (Watts)	Enclosure	W (in.)	D (in.)	H (in.)	Maximum Energy (kJ)
T0F82R3K3	0.82	3,300	EN06	28	13	5	89
T0F82R4K5	0.82	4,500	EN06	28	13	5	271
T0F82R6K7	0.82	6,700	EN09	29	18	8.5	2,357
T0F82R9K0	0.82	9,000	EN09	29	18	8.5	2,357
T0F82R22K4	0.82	22,400	HNS	22	14	40	3,210
T0F82R32K0	0.82	32,000	HWS	26.5	14	40	4,451
T0F82R44K8	0.82	44,800	HND	22	28	40	6,464
T0F82R67K2	0.82	67,200	HNT	22	42	40	9,417
T0F82R86K4	0.82	86,400	HWT	26.5	42	40	12,420
T0F82R128K0	0.82	128,000	2HWWD	53	28	40	17,803
T0F82R153K6	0.82	153,600	2HNNT	44	42	40	22,349
T1F2R2K8	1.2	2,800	EN04	21	13	5	354
T1F2R5K6	1.2	5,600	EN09	29	18	8.5	384
T1F2R14K0	1.2	14,000	EN18	29	18	15.5	2,395
T1F2R28K8	1.2	28,800	HWS	26.5	14	40	4,178
T1F2R57K6	1.2	57,600	HWD	26.5	28	40	7,944
T1F2R96K0	1.2	96,000	HWT	26.5	42	40	13,626
T1F65R2K16	1.65	2,160	EN03	21	10	5	387
T1F65R4K4	1.65	4,400	EN06	28	13	5	761
T1F65R11K0	1.65	11,000	EN18	29	18	15.5	497
T1F8R1K62	1.8	1,620	DB3C	14	10	5	133
T1F8R2K0	1.8	2,000	EN03	21	10	5	207
T1F8R3K3	1.8	3,300	EN03	21	10	5	207
T1F8R4K5	1.8	4,500	EN06	28	13	5	829
T1F8R10K0	1.8	10,000	EN18	29	18	15.5	594
T1F8R19K2	1.8	19,200	HNS	22	14	40	2,648
T1F8R38K4	1.8	38,400	HND	22	28	40	5,587
T1F8R44K8	1.8	44,800	HND	22	28	40	6,452
T1F8R64K0	1.8	64,000	HWD	26.5	28	40	9,030
T1F8R76K8	1.8	76,800	HNT	22	42	40	11,173
T1F8R76K8	1.8	76,800	HNT	22	42	40	11,173
T1F8R144K0	1.8	144,000	2HNNT	44	42	40	21,525
T1F8R288K0	1.8	288,000	3HWWWT	79.5	42	40	41,859
T2F3R1K38	2.3	1,380	EN02	14	13	5	111
T2F3R1K69	2.3	1,690	EN02	14	13	5	170
T2F3R2K75	2.3	2,750	EN04	21	13	5	190
T2F3R3K38	2.3	3,380	EN04	21	13	5	540
T2F3R4K5	2.3	4,500	EN06	28	13	5	1,174
T2F3R6K8	2.3	6,800	EN09	29	18	8.5	1,059
T2F3R8K8	2.3	8,800	EN09	29	18	8.5	1,832
T2F3R13K8	2.3	13,800	EN18	29	18	15.5	759
T2F3R17K0	2.3	17,000	EN18	29	18	15.5	2,722
T2F3R19K2	2.3	19,200	HNS	22	14	40	2,709
T2F3R25K6	2.3	25,600	HNS	22	14	40	3,531
T2F3R28K8	2.3	28,800	HWS	26.5	14	40	4,148
T2F3R32K0	2.3	32,000	HWS	26.5	14	40	4,460
T2F3R44K8	2.3	44,800	HND	22	28	40	6,518
T2F3R57K6	2.3	57,600	HWD	26.5	28	40	8,295
T2F4R6K8	2.4	6,800	EN09	29	18	8.5	1,725
T2F4R13K6	2.4	13,600	EN18	29	18	15.5	792
T2F4R28K8	2.4	28,800	HWS	26.5	14	40	3,972
T2F4R57K6	2.4	57,600	HWD	26.5	28	40	8,381
T2F4R96K0	2.4	96,000	HWT	26.5	42	40	13,950

Standard Resistors

Part Number	Resistance (Ohms)	Power (Watts)	Enclosure	W (in.)	D (in.)	H (in.)	Maximum Energy (kJ)
T2F4R128K0	2.4	128,000	2HWWD	53	28	40	18,100
T2F4R192K0	2.4	192,000	2HWWT	53	42	40	27,650
T2F4R230K4	2.4	230,400	3HNNNT	66	42	40	32,288
T3F3R4K73	3.3	4,730	EN06	28	13	5	272
T3F3R6K26	3.3	6,260	EN09	29	18	8.5	774
T3F3R9K46	3.3	9,460	EN18	29	18	15.5	1,520
T3F3R11K3	3.3	11,300	EN18	29	18	15.5	636
T3F3R22K4	3.3	22,400	HNS	22	14	40	3,212
T3F3R32K0	3.3	32,000	HWS	26.5	14	40	4,484
T3F3R44K8	3.3	44,800	HND	22	28	40	6,464
T3F3R64K0	3.3	64,000	HWD	26.5	28	40	9,250
T3F3R86K4	3.3	86,400	HWT	26.5	42	40	12,392
T3F3R115K2	3.3	115,200	2HWWD	53	28	40	16,400
T3F3R128K0	3.3	128,000	2HWWD	53	28	40	18,100
T3F3R153K6	3.3	153,600	2HNNT	44	42	40	22,349
T3F3R192K0	3.3	192,000	2HWWT	53	42	40	27,652
T3F3R259K2	3.3	259,200	3HWWWT	79.5	42	40	37,300
T3F5R3K4	3.5	3,400	EN04	21	13	5	447
T3F5R4K5	3.5	4,500	EN06	28	13	5	821
T3F5R8K6	3.5	8,600	EN09	29	18	8.5	934
T3F5R22K4	3.5	22,400	HNS	22	14	40	3,226
T3F5R44K8	3.5	44,800	HND	22	28	40	6,453
T3F5R64K0	3.5	64,000	HWD	26.5	28	40	9,300
T3F5R86K4	3.5	86,400	HWT	26.5	42	40	12,347
T3F5R128K0	3.5	128,000	2HWWD	53	28	40	17,400
T3F5R153K6	3.5	153,600	2HNNT	44	42	40	22,347
T4F4R720W	4.4	720	EN01	14	7	5	53
T4F4R1K08	4.4	1,080	DB3C	14	10	5	53
T4F4R1K44	4.4	1,440	EN02	14	13	5	91
T4F4R2K75	4.4	2,750	EN04	21	13	5	325
T4F4R4K5	4.4	4,500	EN06	28	13	5	507
T4F4R6K52	4.4	6,520	EN09	29	18	8.5	1,032
T4F4R10K9	4.4	10,900	EN18	29	18	15.5	817
T4F4R13K5	4.4	13,500	EN18	29	18	15.5	2,027
T4F4R22K4	4.4	22,400	HNS	22	14	40	3,701
T4F4R28K8	4.4	28,800	HWS	26.5	14	40	4,148
T4F4R44K8	4.4	44,800	HND	22	28	40	6,378
T4F4R57K6	4.4	57,600	HWD	26.5	28	40	8,311
T4F4R86K4	4.4	86,400	HWT	26.5	42	40	12,165
T4F4R96K0	4.4	96,000	HWT	26.5	42	40	13,618
T4F4R115K2	4.4	115,200	2HWWD	53	28	40	17,000
T4F4R172K8	4.4	172,800	2HWWT	53	42	40	25,500
T4F4R201K6	4.4	201,600	3HNNNT	66	42	40	29,333
T4F6R1K08	4.6	1,080	DB3C	14	10	5	55
T4F6R1K8	4.6	1,800	EN03	21	10	5	71
T4F6R2K16	4.6	2,160	EN03	21	10	5	240
T4F6R3K44	4.6	3,440	EN04	21	13	5	339
T4F6R4K50	4.6	4,500	EN09	29	18	8.5	530
T4F6R6K64	4.6	6,640	EN09	29	18	8.5	809
T4F6R15K6	4.6	15,600	EN18	29	18	15.5	1,591
T4F6R22K4	4.6	22,400	HNS	22	14	40	3,259
T4F6R32K0	4.6	32,000	HWS	26.5	14	40	4,589
T4F6R44K8	4.6	44,800	HND	22	28	40	6,355

Standard Resistors

Part Number	Resistance (Ohms)	Power (Watts)	Enclosure	W (in.)	D (in.)	H (in.)	Maximum Energy (kJ)
T4F6R64K0	4.6	64,000	HWD	26.5	28	40	9,251
T4F6R115K2	4.6	115,200	2HWWD	53	28	40	16,591
T4F8R820W	4.8	820	DB3C	14	10	5	43
T4F8R1K63	4.8	1,630	EN02	14	13	5	99
T4F8R2K88	4.8	2,880	EN04	21	13	5	176
T4F8R4K07	4.8	4,070	EN06	28	13	5	174
T4F8R6K51	4.8	6,510	EN09	29	18	8.5	396
T4F8R8K13	4.8	8,130	EN09	29	18	8.5	1,281
T4F8R14K0	4.8	14,000	EN18	29	18	15.5	2,211
T4F8R19K2	4.8	19,200	HNS	22	14	40	2,784
T4F8R32K0	4.8	32,000	HWS	26.5	14	40	4,589
T4F8R57K6	4.8	57,600	HWD	26.5	28	40	8,280
T4F8R96K0	4.8	96,000	HWT	26.5	42	40	13,516
T6F3R2K55	6.3	2,550	EN04	21	13	5	130
T6F3R4K88	6.3	4,880	EN06	28	13	5	726
T6F3R6K80	6.3	6,800	EN09	29	18	8.5	726
T6F3R13K6	6.3	13,600	EN18	29	18	15.5	4,528
T6F3R19K2	6.3	19,200	HNS	22	14	40	2,760
T6F3R28K8	6.3	28,800	HWS	26.5	14	40	4,186
T6F3R32K0	6.3	32,000	HWS	26.5	14	40	4,656
T6F3R57K6	6.3	57,600	HWD	26.5	28	40	8,140
T6F3R67K2	6.3	67,200	HNT	22	42	40	8,894
T6F3R115K2	6.3	115,200	2HWWD	53	28	40	16,743
T6F3R128K0	6.3	128,000	2HWWD	53	28	40	18,624
T7R720W	7	720	EN01	14	7	5	29
T7R1K44	7	1,120	DB3C	14	10	5	84
T7R2K23	7	2,230	EN03	21	10	5	144
T7R4K73	7	4,730	EN06	28	13	5	807
T7R5K58	7	5,580	EN09	29	18	8.5	807
T7R8K32	7	8,320	EN18	29	18	15.5	807
T7R14K9	7	14,900	EN18	29	18	15.5	578
T7R19K2	7	19,200	HNS	22	14	40	2,744
T7R25K6	7	25,600	HNS	22	14	40	3,706
T7R28K8	7	28,800	HWS	26.5	14	40	4,175
T7R38K4	7	38,400	HND	22	28	40	5,164
T7R51K2	7	51,200	HND	22	28	40	7,101
T7R57K6	7	57,600	HWD	26.5	28	40	8,049
T7R67K2	7	67,200	HNT	22	42	40	8,788
T7R76K8	7	76,800	HNT	22	42	40	10,206
T7R96K0	7	96,000	HWT	26.5	42	40	13,061
T7R115K2	7	115,200	2HWWD	53	28	40	16,702
T7R134K4	7	134,400	2HNNT	44	42	40	18,852
T7R153K6	7	153,600	2HNNT	44	42	40	21,788
T8R700W	8	700	EN01	14	7	5	46
T8R1K08	8	1,080	DB3C	14	10	5	65
T8R1K80	8	1,800	EN03	21	10	5	107
T8R2K4	8	2,400	EN04	21	13	5	165
T8R4K8	8	4,800	EN06	28	13	5	590
T8R6K6	8	6,600	EN09	29	18	8.5	1,022
T8R8K0	8	8,000	EN09	29	18	8.5	950
T8R13K6	8	13,600	EN18	29	18	15.5	2,367
T8R19K2	8	19,200	HNS	22	14	40	2,361
T8R28K8	8	28,800	HWS	26.5	14	40	4,160

Standard Resistors

<u>Part Number</u>	<u>Resistance (Ohms)</u>	<u>Power (Watts)</u>	<u>Enclosure</u>	<u>W (in.)</u>	<u>D (in.)</u>	<u>H (in.)</u>	<u>Maximum Energy (kJ)</u>
T8R38K4	8	38,400	HND	22	28	40	5,164
T8R51K2	8	51,200	HND	22	28	40	6,990
T8R64K0	8	64,000	HWD	26.5	28	40	9,000
T8F5R360W	8.5	360	EN00	14	4	5	31
T8F5R720W	8.5	720	EN01	14	7	5	79
T8F5R2K0	8.5	2,000	EN02	14	13	5	175
T9F3R360W	9.3	360	EN00	14	4	5	34
T9F3R720W	9.3	720	EN01	14	7	5	54
T9F3R1K08	9.3	1,080	DB3C	14	10	5	76
T9F3R2K1	9.3	2,100	EN03	21	10	5	121
T9F3R2K75	9.3	2,750	EN04	21	13	5	192
T9F3R4K2	9.3	4,200	EN06	28	13	5	424
T9F3R6K88	9.3	6,880	EN09	29	18	8.5	1,072
T9F3R11K0	9.3	11,000	EN18	29	18	15.5	768
T9F3R13K5	9.3	13,500	EN18	29	18	15.5	768
T9F3R16K8	9.3	16,800	EN18	29	18	15.5	2,482
T9F3R22K4	9.3	22,400	HNS	22	14	40	3,177
T9F3R38K4	9.3	38,400	HND	22	28	40	5,022
T9F3R51K2	9.3	51,200	HND	22	28	40	6,912
T9F3R67K2	9.3	67,200	HNT	22	42	40	8,505
T9F3R96K0	9.3	96,000	HWT	26.5	42	40	12,706
T10R720W	10	720	EN01	14	7	5	58
T10R1K08	10	1,080	DB3C	14	10	5	41
T10R1K37	10	1,370	EN02	14	13	5	92
T10R1K88	10	1,880	EN03	21	10	5	121
T10R2K73	10	2,730	EN04	21	13	5	121
T10R4K5	10	4,500	EN06	28	13	5	455
T10R11K0	10	11,000	EN18	29	18	15.5	482
T10R14K1	10	14,100	EN18	29	18	15.5	2,346
T10R19K2	10	19,200	HNS	22	14	40	2,673
T10R28K8	10	28,800	HWS	26.5	14	40	4,131
T10R38K4	10	38,400	HND	22	28	40	4,961
T10R51K2	10	51,200	HND	22	28	40	6,858
T10R67K2	10	67,200	HNT	22	42	40	8,398
T11R360W	11	360	EN00	14	4	5	25
T11R720W	11	720	EN01	14	7	5	40
T11R1K38	11	1,380	EN02	14	13	5	101
T11R1K76	11	1,760	EN03	21	10	5	143
T11R2K82	11	2,820	EN04	21	13	5	133
T11R3K52	11	3,520	EN06	28	13	5	227
T11R7K4	11	7,400	EN09	29	18	8.5	812
T11R14K1	11	14,100	EN18	29	18	15.5	2,581
T14R360W	14	360	EN00	14	4	5	20
T14R720W	14	720	EN01	14	7	5	51
T14R1K08	14	1,080	DB3C	14	10	5	129
T14R1K95	14	1,950	EN03	21	10	5	114
T14R4K8	14	4,800	EN06	28	13	5	289
T14R6K8	14	6,800	EN09	29	18	8.5	324
T14R12K6	14	12,600	EN18	29	18	15.5	1,033
T15F4R360W	15.4	360	EN00	14	4	5	22
T15F4R720W	15.4	720	EN01	14	7	5	56
T15F4R1K08	15.4	1,080	DB3C	14	10	5	99
T15F4R1K44	15.4	1,440	EN02	14	13	5	89

Standard Resistors

<u>Part Number</u>	<u>Resistance (Ohms)</u>	<u>Power (Watts)</u>	<u>Enclosure</u>	<u>W (in.)</u>	<u>D (in.)</u>	<u>H (in.)</u>	<u>Maximum Energy (kJ)</u>
T15F4R2K16	15.4	2,160	EN03	21	10	5	126
T15F4R2K88	15.4	2,880	EN04	21	13	5	225
T15F4R6K6	15.4	6,600	EN09	29	18	8.5	261
T15F4R13K5	15.4	13,500	EN18	29	18	15.5	1,775
T15F4R25K6	15.4	25,600	HNS	22	14	40	3,510
T15F4R44K8	15.4	44,800	HND	22	28	40	5,599
T15F4R51K2	15.4	51,200	HND	22	28	40	6,507
T16R360W	16	360	EN00	14	4	5	23
T16R720W	16	720	EN01	14	7	5	58
T16R1K08	16	1,080	DB3C	14	10	5	52
T16R2K16	16	2,160	EN03	21	10	5	130
T16R2K88	16	2,880	EN04	21	13	5	234
T16R6K0	16	6,000	EN09	29	18	8.5	370
T16R9K0	16	9,000	EN18	29	18	15.5	729
T16R11K5	16	11,500	EN18	29	18	15.5	1,100
T16R19K2	16	19,200	HNS	22	14	40	2,531
T16R22K4	16	22,400	HNS	22	14	40	3,000
T16R32K0	16	32,000	HWS	26.5	14	40	4,438
T16R44K8	16	44,800	HND	22	28	40	5,504
T17R360W	17	360	EN00	14	4	5	23
T17R720W	17	720	EN01	14	7	5	58
T17R1K08	17	1,080	DB3C	14	10	5	55
T17R1K5	17	1,500	EN02	14	13	5	98
T17R2K16	17	2,160	EN03	21	10	5	139
T17R2K88	17	2,880	EN04	21	13	5	248
T17R4K32	17	4,320	EN06	28	13	5	154
T17R5K05	17	5,050	EN09	29	18	8.5	351
T17R6K5	17	6,500	EN09	29	18	8.5	393
T17R10K0	17	10,000	EN18	29	18	15.5	774
T17R11K2	17	11,200	EN18	29	18	15.5	1,254
T17R19K2	17	19,200	HNS	22	14	40	2,531
T17R22K4	17	22,400	HNS	22	14	40	3,000
T17R32K0	17	32,000	HWS	26.5	14	40	4,438
T17R44K8	17	44,800	HND	22	28	40	5,504
T18R1K08	18	1,080	DB3C	14	10	5	65
T18R1K8	18	1,800	EN03	21	10	5	92
T18R2K16	18	2,160	EN03	21	10	5	163
T18R2K75	18	2,750	EN04	21	13	5	263
T18R3K6	18	3,600	EN06	28	13	5	217
T18R6K72	18	6,720	EN09	29	18	8.5	371
T18R10K8	18	10,800	EN18	29	18	15.5	651
T18R13K4	18	13,400	EN18	29	18	15.5	1,328
T18R19K2	18	19,200	HNS	22	14	40	2,511
T18R25K6	18	25,600	HNS	22	14	40	3,456
T18R28K8	18	28,800	HWS	26.5	14	40	3,933
T18R38K4	18	38,400	HND	22	28	40	4,576
T18R44K8	18	44,800	HND	22	28	40	5,457
T18R51K2	18	51,200	HND	22	28	40	6,372
T18R57K6	18	57,600	HWD	26.5	28	40	7,290
T18R64K0	18	64,000	HWD	26.5	28	40	8,201
T18R76K8	18	76,800	HNT	22	42	40	8,950
T18R96K0	18	96,000	HWT	26.5	42	40	11,643
T19R720W	19	720	EN01	14	7	5	69

Standard Resistors

Part Number	Resistance (Ohms)	Power (Watts)	Enclosure	W (in.)	D (in.)	H (in.)	Maximum Energy (kJ)
T19R1K08	19	1,080	DB3C	14	10	5	62
T19R1K44	19	1,440	EN02	14	13	5	110
T19R1K87	19	1,870	EN03	21	10	5	98
T19R2K47	19	2,470	EN04	21	13	5	344
T19R4K11	19	4,110	EN06	28	13	5	229
T19R6K57	19	6,570	EN09	29	18	8.5	392
T19R8K22	19	8,220	EN09	29	18	8.5	392
T19R13K6	19	13,600	EN18	29	18	15.5	2,190
T19R22K4	19	22,400	HNS	22	14	40	2,965
T19R25K6	19	25,600	HNS	22	14	40	3,442
T19R32K0	19	32,000	HWS	26.5	14	40	4,404
T19R44K8	19	44,800	HND	22	28	40	5,410
T21R360W	21	360	EN00	14	4	5	30
T21R720W	21	720	EN01	14	7	5	48
T21R1K08	21	1,080	DB3C	14	10	5	123
T21R2K80	21	2,800	EN04	21	13	5	214
T21R4K5	21	4,500	EN06	28	13	5	273
T21R10K4	21	10,400	EN18	29	18	15.5	1,549
T23R360W	23	360	EN00	14	4	5	21
T23R720W	23	720	EN01	14	7	5	33
T23R1K08	23	1,080	DB3C	14	10	5	47
T23R1K44	23	1,440	EN02	14	13	5	83
T23R1K8	23	1,800	EN03	21	10	5	213
T23R2K16	23	2,160	EN03	21	10	5	211
T23R2K88	23	2,880	EN04	21	13	5	336
T23R4K98	23	4,980	EN06	28	13	5	277
T23R6K84	23	6,840	EN09	29	18	8.5	1,307
T25R360W	25	360	EN00	14	4	5	23
T25R720W	25	720	EN01	14	7	5	36
T25R1K08	25	1,080	DB3C	14	10	5	91
T25R1K44	25	1,440	EN02	14	13	5	91
T25R2K16	25	2,160	EN03	21	10	5	231
T25R2K7	25	2,700	EN04	21	13	5	144
T25R4K34	25	4,340	EN06	28	13	5	325
T25R6K25	25	6,250	EN09	29	18	8.5	301
T25R9K76	25	9,760	EN18	29	18	15.5	516
T25R13K6	25	13,600	EN18	29	18	15.5	1,844
T25R19K2	25	19,200	HNS	22	14	40	2,410
T25R22K4	25	22,400	HNS	22	14	40	2,870
T25R25K6	25	25,600	HNS	22	14	40	3,334
T25R32K0	25	32,000	HWS	26.5	14	40	4,286
T25R44K8	25	44,800	HND	22	28	40	5,174
T28R360W	28	360	EN00	14	4	5	16
T28R720W	28	720	EN01	14	7	5	40
T28R1K08	28	1,080	DB3C	14	10	5	102
T28R1K44	28	1,440	EN02	14	13	5	113
T28R2K79	28	2,790	EN04	21	13	5	162
T28R4K46	28	4,460	EN06	28	13	5	409
T28R6K28	28	6,280	EN09	29	18	8.5	338
T28R10K1	28	10,100	EN18	29	18	15.5	558
T28R13K0	28	13,000	EN18	29	18	15.5	1,275
T28R22K4	28	22,400	HNS	22	14	40	2,835
T28R25K6	28	25,600	HNS	22	14	40	3,294

Standard Resistors

Part Number	Resistance (Ohms)	Power (Watts)	Enclosure	W (in.)	D (in.)	H (in.)	Maximum Energy (kJ)
T29R720W	29	720	EN01	14	7	5	42
T29R1K44	29	1,440	EN02	14	13	5	106
T29R4K4	29	4,400	EN06	28	13	5	237
T29R25K6	29	25,600	HNS	22	14	40	3,280
T32R360W	32	360	EN00	14	4	5	18
T32R720W	32	720	EN01	14	7	5	46
T32R1K08	32	1,080	DB3C	14	10	5	73
T32R1K44	32	1,440	EN02	14	13	5	117
T32R2K16	32	2,160	EN03	21	10	5	186
T32R2K88	32	2,880	EN04	21	13	5	185
T32R4K0	32	4,000	EN06	28	13	5	294
T32R5K6	32	5,600	EN09	29	18	8.5	467
T32R6K5	32	6,500	EN09	29	18	8.5	518
T32R9K51	32	9,510	EN18	29	18	15.5	660
T32R12K7	32	12,700	EN18	29	18	15.5	660
T32R19K2	32	19,200	HNS	22	14	40	2,329
T32R25K6	32	25,600	HNS	22	14	40	3,240
T34R720W	34	720	EN01	14	7	5	49
T34R1K44	34	1,440	EN02	14	13	5	124
T34R3K6	34	3,600	EN06	28	13	5	196
T34R6K8	34	6,800	EN18	29	18	15.5	410
T36R360W	36	360	EN00	14	4	5	21
T36R720W	36	720	EN01	14	7	5	33
T36R1K08	36	1,080	DB3C	14	10	5	83
T36R1K44	36	1,440	EN02	14	13	5	131
T36R2K88	36	2,880	EN04	21	13	5	130
T36R4K63	36	4,630	EN06	28	13	5	330
T36R5K72	36	5,720	EN09	29	18	8.5	206
T36R11K3	36	11,300	EN18	29	18	15.5	743
T36R19K2	36	19,200	HNS	22	14	40	2,288
T36R25K6	36	25,600	HNS	22	14	40	3,186
T40R360W	40	360	EN00	14	4	5	23
T40R720W	40	720	EN01	14	7	5	58
T40R1K08	40	1,080	DB3C	14	10	5	58
T40R1K44	40	1,440	EN02	14	13	5	91
T40R2K16	40	2,160	EN03	21	10	5	146
T40R2K88	40	2,880	EN04	21	13	5	145
T40R3K96	40	3,960	EN06	28	13	5	367
T40R4K32	40	4,320	EN06	28	13	5	367
T40R5K86	40	5,860	EN09	29	18	8.5	365
T40R6K85	40	6,850	EN09	29	18	8.5	438
T40R9K92	40	9,920	EN18	29	18	15.5	482
T40R10K2	40	10,200	EN18	29	18	15.5	482
T40R13K0	40	13,000	EN18	29	18	15.5	825
T40R19K2	40	19,200	HNS	22	14	40	2,248
T40R19K2	40	19,200	HNS	22	14	40	2,248
T40R22K4	40	22,400	HNS	22	14	40	2,693
T43R720W	43	720	EN01	14	7	5	39
T43R1K44	43	1,440	EN02	14	13	5	62
T43R3K92	43	3,920	EN06	28	13	5	221
T43R5K11	43	5,110	EN09	29	18	8.5	155
T43R11K0	43	11,000	EN18	29	18	15.5	518
T43R19K2	43	19,200	HNS	22	14	40	2,217

Standard Resistors

<u>Part Number</u>	<u>Resistance (Ohms)</u>	<u>Power (Watts)</u>	<u>Enclosure</u>	<u>W (in.)</u>	<u>D (in.)</u>	<u>H (in.)</u>	<u>Maximum Energy (kJ)</u>
T45R360W	45	360	EN00	14	4	5	16
T45R720W	45	720	EN01	14	7	5	41
T45R1K08	45	1,080	DB3C	14	10	5	65
T45R1K44	45	1,440	EN02	14	13	5	103
T45R2K16	45	2,160	EN03	21	10	5	164
T45R2K88	45	2,880	EN04	21	13	5	163
T45R4K68	45	4,680	EN06	28	13	5	260
T45R6K0	45	6,000	EN09	29	18	8.5	413
T45R11K0	45	11,000	EN18	29	18	15.5	542
T45R13K3	45	13,300	EN18	29	18	15.5	929
T45R19K2	45	19,200	HNS	22	14	40	2,197
T48R360W	48	360	EN00	14	4	5	17
T48R720W	48	720	EN01	14	7	5	44
T48R1K44	48	1,440	EN02	14	13	5	43
T48R2K52	48	2,520	EN04	21	13	5	279
T53R360W	53	360	EN00	14	4	5	19
T53R720W	53	720	EN01	14	7	5	48
T53R1K08	53	1,080	DB3C	14	10	5	77
T53R1K44	53	1,440	EN02	14	13	5	77
T53R1K8	53	1,800	EN03	21	10	5	122
T53R2K16	53	2,160	EN03	21	10	5	193
T53R2K88	53	2,880	EN04	21	13	5	192
T53R4K8	53	4,800	EN06	28	13	5	307
T53R6K8	53	6,800	EN09	29	18	8.5	486
T53R10K0	53	10,000	EN18	29	18	15.5	639
T53R12K0	53	12,000	EN18	29	18	15.5	690
T53R19K2	53	19,200	HNS	22	14	40	1,530
T60R360W	60	360	EN00	14	4	5	14
T60R720W	60	720	EN01	14	7	5	34
T60R1K08	60	1,080	DB3C	14	10	5	54
T60R1K44	60	1,440	EN02	14	13	5	45
T60R1K8	60	1,800	EN03	21	10	5	138
T60R2K16	60	2,160	EN03	21	10	5	138
T60R2K52	60	2,520	EN04	21	13	5	219
T60R4K47	60	4,470	EN06	28	13	5	217
T60R5K5	60	5,500	EN09	29	18	8.5	182
T60R6K85	60	6,850	EN18	29	18	15.5	555
T60R9K92	60	9,920	EN18	29	18	15.5	876
T60R10K0	60	10,000	EN18	29	18	15.5	723
T60R19K2	60	19,200	HNS	22	14	40	1,499
T67R360W	67	360	EN00	14	4	5	15
T67R720W	67	720	EN01	14	7	5	38
T67R1K08	67	1,080	DB3C	14	10	5	61
T67R1K8	67	1,800	EN03	21	10	5	97
T67R2K52	67	2,520	EN04	21	13	5	245
T67R3K29	67	3,290	EN06	28	13	5	245
T67R5K76	67	5,760	EN09	29	18	8.5	388
T67R9K26	67	9,260	EN18	29	18	15.5	615
T67R13K0	67	13,000	EN18	29	18	15.5	734
T77R360W	77	360	EN00	14	4	5	17
T77R720W	77	720	EN01	14	7	5	44
T77R1K08	77	1,080	DB3C	14	10	5	70
T77R1K44	77	1,440	EN02	14	13	5	70

Standard Resistors

<u>Part Number</u>	<u>Resistance (Ohms)</u>	<u>Power (Watts)</u>	<u>Enclosure</u>	<u>W (in.)</u>	<u>D (in.)</u>	<u>H (in.)</u>	<u>Maximum Energy (kJ)</u>
T77R2K16	77	2,160	EN03	21	10	5	177
T77R4K32	77	4,320	EN06	28	13	5	174
T77R5K7	77	5,700	EN09	29	18	8.5	445
T77R9K1	77	9,100	EN18	29	18	15.5	706
T97R360W	97	360	EN00	14	4	5	14
T97R720W	97	720	EN01	14	7	5	22
T97R1K08	97	1,080	DB3C	14	10	5	55
T97R1K44	97	1,440	EN02	14	13	5	88
T97R1K8	97	1,800	EN03	21	10	5	140
T97R2K16	97	2,160	EN03	21	10	5	140
T97R2K88	97	2,880	EN04	21	13	5	222
T97R4K32	97	4,320	EN06	28	13	5	354
T97R6K48	97	6,480	EN09	29	18	8.5	352
T97R10K0	97	10,000	EN18	29	18	15.5	349
T121R360W	121	360	EN00	14	4	5	11
T121R720W	121	720	EN01	14	7	5	44
T121R1K08	121	1,080	DB3C	14	10	5	69
T121R1K44	121	1,440	EN02	14	13	5	69
T121R1K8	121	1,800	EN03	21	10	5	175
T121R2K16	121	2,160	EN03	21	10	5	110
T121R2K52	121	2,520	EN04	21	13	5	175
T121R3K24	121	3,240	EN06	28	13	5	175
T121R5K61	121	5,610	EN09	29	18	8.5	442

Case Resistors

Part Number	<u>Resistance</u> (Ohms)	<u>Power</u> (Watts)	<u>Enclosure</u>	<u>W (in.)</u>	<u>D (in.)</u>	<u>H (in.)</u>	<u>Maximum</u> Energy (kJ)
TC15R240W	15	240	RFP-H-300	8.5	2.4	1.2	11.4
TC18R200W	18	200	RFP-H-200	6.6	2.4	1.2	5.4
TC18R370W	18	370	RFP-H-500	13.3	2.4	1.2	21.8
TC21R200W	21	200	RFP-H-200	6.6	2.4	1.2	5.4
TC21R240W	21	240	RFP-H-300	8.5	2.4	1.2	13.6
TC21R370W	21	370	RFP-H-500	13.3	2.4	1.2	34.3
TC27R200W	27	200	RFP-H-200	6.6	2.4	1.2	3.2
TC27R240W	27	240	RFP-H-300	8.5	2.4	1.2	8.1
TC27R370W	27	370	RFP-H-500	13.3	2.4	1.2	20.6
TC32R200W	32	200	RFP-H-200	6.6	2.4	1.2	3.8
TC32R240W	32	240	RFP-H-300	8.5	2.4	1.2	9.6
TC36R200W	36	200	RFP-H-200	6.6	2.4	1.2	4.3
TC36R370W	36	370	RFP-H-500	13.3	2.4	1.2	17.2
TC39R200W	39	200	RFP-H-200	6.6	2.4	1.2	2.9
TC39R370W	39	370	RFP-H-500	13.3	2.4	1.2	18.7
TC47R200W	47	200	RFP-H-200	6.6	2.4	1.2	3.5
TC47R240W	47	240	RFP-H-300	8.5	2.4	1.2	8.9
TC47R370W	47	370	RFP-H-500	13.3	2.4	1.2	22.5
TC53R300W	53	300	RFP-H-400	10.5	2.4	1.2	10.0
TC53R370W	53	370	RFP-H-500	13.3	2.4	1.2	21.6
TC68R200W	68	200	RFP-H-200	6.6	2.4	1.2	2.0
TC68R240W	68	240	RFP-H-300	8.5	2.4	1.2	6.9
TC68R370W	68	370	RFP-H-500	13.3	2.4	1.2	20.5
TC80R200W	80	200	RFP-H-200	6.6	2.4	1.2	2.4
TC80R240W	80	240	RFP-H-300	8.5	2.4	1.2	6.0
TC80R370W	80	370	RFP-H-500	13.3	2.4	1.2	15.1
TC117R200W	117	200	RFP-H-200	6.6	2.4	1.2	3.2
TC117R240W	117	240	RFP-H-300	8.5	2.4	1.2	8.1
TC117R300W	117	300	RFP-H-400	10.5	2.4	1.2	8.7
TC117R370W	117	370	RFP-H-500	13.3	2.4	1.2	13.9